



Admiral Radio



PARTS LIST & SCHEMATIC DIAGRAM FOR STEREOPHONIC PHONOGRAPH MODEL PS4A2

RESISTORS

R1A 1.5 meg. loudness Control.....	C571
R1B 1.5 meg. loudness Control.....	C571
R2 100K ohm. $\frac{1}{2}$ W.....	60B8-104
R3 100K ohm. $\frac{1}{2}$ W.....	60B8-104
R4A 2 meg. Tone Control.....	C572
R4B 2 meg. Tone Control.....	C572
R5 820K ohm $\frac{1}{2}$ W.....	60B8-824
R6 820K ohm $\frac{1}{2}$ W.....	60B8-824
R7 470K ohm $\frac{1}{2}$ W.....	60B8-474
R8 470K ohm $\frac{1}{2}$ W.....	60B8-474
R9A 1 meg. Balance Control.....	C573
R9B 1 meg. Balance Control.....	C573
R10 3300 ohm $\frac{1}{2}$ W.....	60B8-332
R11 47 ohm $\frac{1}{2}$ W.....	60B14-470
R12 4700 ohm 1W.....	60B14-472
R13 150 ohms $\frac{1}{2}$ W.....	60B8-151
R14 150 ohms $\frac{1}{2}$ W.....	60B8-151

CAPACITORS

C1 .022 mfd. 400V Cond.....	64B8-30
C2 .022 mfd. 400V Cond.....	64B8-30
C3 .0015 mfd. Ceramic.....	65A17-2
C4 .0015 mfd. Ceramic.....	65A17-2
C5 .0022 mfd. 600V Cond.....	64B8-17
C6 .047 mfd. 400V Cond.....	64B8-28
C7 .047 mfd. 400V Cond.....	64B8-28
C8 .0022 mfd. 600V Cond.....	64B8-17
C9 .01 mfd. 400V Cond.....	64B5-10
C10 .01 mfd. 400V Cond.....	64B5-10
C11 .047 mfd. 600V Cond.....	64B8-9
C12 5 mfd. 50V Cond.....	67W4-5
C13A 80 mfd. Electrolytic.....	C574
C13B 80 mfd. Electrolytic.....	C574
C14 5 mfd. 20V Cond.....	67K3-1
C15 5 mfd. 20V Cond.....	67K3-1
C16 .1 mfd. 600V Cond.....	64B8-7

TRANSFORMERS AND RECTIFIERS

T1 & T2 Output x former.....C575

Selenium Rect.....C576

CABINET PARTS PS4A2

Master Cabinet	35P118-1
Speaker Unit Cabinet	35P118-2
Hinge(master cabinet)	37K18-1
Hinge(Speaker Unit)	37K20-1
Studs	27K4-1
Catch	37K14-1
Handle	37K19-3
Monogram	26X58-2
Hitch Bracket(line Cd.)	15K29-1
Plastic Foot	37K16-1
Knobs(black)	C557
Speaker 10"	C577
Speaker 4"	C546

Speaker Jack(Female)	88A1
Speaker Plug (Male)	88A2-3
Remote Speaker Leads	15'89L4-1
Wire Connectors	C570
Collaro Stereo Changer	9400L1-2
Stereo Cartridge	409B33-1-1
Stylus (78)	98C15-101
Stylus (LP)	98C15-100

For a complete changer, Parts List refer to Collaro Conquest Changer Manual.

