

RESISTORS

Item #	Resistance	Part #
Variable		
R1	1,000,000 Ohm L.C.	13402
R2	10,000,000 Ohm T.C.	13400
Graphite		
R4	100,000 Ohm	40531
R5	150 Ohm	33313
R6	100,000 Ohm	40531
R7	50,000 Ohm	33301
R8	20,000 Ohm	40542
R9	20,000 Ohm	40546
R11	500,000 Ohm	33303
R12	400 Ohm	33310
R13	400 Ohm	33310
R14	1,000 Ohm	33315
R15	500,000 Ohm	33303
R16	500,000 Ohm	33303
R17	50,000 Ohm	33301
R18	50,000 Ohm	33301
R19	50,000 Ohm	33301
R20	750 Ohm	40543
R21	50,000 Ohm	33301
R22	50,000 Ohm	33301
R32	2,000 Ohm	33319
R33	50,000 Ohm	33301
R34	10,000 Ohm	33318
Wire found		
R35	1,180 Ohm	
R36	3,600 Ohm	Candohm
R37	10,000 Ohm	13554
R38	10,000 Ohm	
R39	20,000 Ohm	

CONDENSERS

Item #	Capacitance	Part #
C7	S.W. Int. P. Pad.)	
C8	P.C. Int. P. Pad.)	5353
C9	B.C. Int. P. Pad.)	
C10	S.W. Osc. Pad.)	
C11	P.C. Osc. Pad.)	5353
C12	B.C. Osc. Pad.)	
C13	S.W. Osc. S. Pad.)	
C14	F.C. Osc. S. Pad.)	5287
C15	B.C. Osc. S. Pad.	4670
C16	1st I. F. Pad.)	4639
C17	1st I. F. Pad.)	
C18	2nd I. F. Pad.)	4639
C19	2nd I. F. Pad.)	
C20	3rd I. F. Pad.)	4639
C21	3rd I. F. Pad.)	
C22	3rd I. F. Pad.	12404
Tubular		
C25	0.05 mf. 200 V.	38102
C26	0.1 mf. 200 V.	38106
C27	0.05 mf. 200 V.	38102
C28	0.1 mf. 200 V.	38106
C29	0.1 mf. 400 V.	38121
C30	0.05 mf. 200 V.	38102
C31	0.1 mf. 200 V.	38106
C32	0.05 mf. 200 V.	38102
C33	0.1 mf. 200 V.	38106
C34	0.05 mf. 200 V.	38102
C36	0.25 mf. 200 V.	38107
C38	0.25 mf. 400 V.	38127
C39	0.005 mf. 600 V.	38110
C40	0.0015 mf. 800 V.	11977
C41	0.5 mf. 200 V.	38108
C47	0.1 mf. 200 V.	38106
C48	0.5 mf. 200 V.	38108
Mica		
C50	200 mmf.	37905
C51	100 mmf.	37906
C52	1,500 mmf.	34122
C53	200 mmf.	37908
C54	50 mmf.	37904
C56	200 mmf.	37902
C57	100 mmf.	37906

CONDENSERS

Item #	Capacitance	Part #
C63	30 mf. Wet	39813
C64	30 mf. Wet	13014
C65	2 mf. Dry)	
C66	4 mf. Dry)	13085
C67	4 mf. Dry)	
C70	Neutralizing Capacity.	

TRANSFORMERS

Item #	Description	Part #
T1	S.W. Ant. Trans.	5279
T2	P.C. Ant. Trans.	5278
T3	B.C. Ant. Trans.	5277
T4	S.W. Int. Trans.	5283
T5	P.C. Int. Trans.	5282
T6	B.C. Int. Ptl.	5281
T7	B.C. Int. Sec.	5280
T8	S.W. Osc. Trans.	5286
T9	P.C. Osc. Trans.	5285
T10	B.C. Osc. Trans.	5284
T11	1st I. F. Trans.	5257
T12	2nd I. F. Trans.	5257
T13	3rd I. F. Trans.	5007
T14	1st A. F. Trans.	5333
T15	Power Trans.	5335
T16	Output Trans.	5413
T17	Speaker	6412

Parts List

Rogers 11/10P Radio Phono
(Chassis 6R1031)

R1
VOLUME
CONTROL
S2
LINE
SWITCH

C15 - 580 KC.
OSC. SERIES ALIGN

C12 - 1500 KC.
OSC. ALIGNING

C11 - 5.0 MCS.
OSC. ALIGNING

C9 - 1500 KC.
R.F. ALIGNING

C8 - 5.0 MCS.
R.F. ALIGNING

C7 - 17.8 MCS.
R.F. ALIGNING

C6 - 1500 KC.
ANT. ALIGNING

C5 - 5.0 MCS.
ANT. ALIGNING

C4 - 17.8 MCS.
ANT. ALIGNING

6A7M

OSC. SERIES ALIGN
C14 - C13
1.8 MCS - 6.0 MCS
(NUT) (SCREW)

OSC. MOD. 1
1/2 DETECTOR

2.5 I.F. TRANS.

456 KC. ALIGNING

6K7M

1.5 I.F. AMP.

456 KC. ALIGNING

2.5 I.F. TRANS.

456 KC. ALIGNING

6K7M

1.5 I.F. AMP.

456 KC. ALIGNING

2.5 I.F. TRANS.

456 KC. ALIGNING

6K7M

1.5 I.F. AMP.

456 KC. ALIGNING

2.5 I.F. TRANS.

456 KC. ALIGNING

6K7M

1.5 I.F. AMP.

456 KC. ALIGNING

2.5 I.F. TRANS.

456 KC. ALIGNING

6F7M

1.5 I.F. AMP.

456 KC. ALIGNING

R2 TONE CONTROL &
I.F. EXPANDER CONTROL

T15

H13594
GREEN - 25 CYC.
13595
RED - 60 CYC.

C63

C64

RECTIFIER

POWER OUTPUT

POWER OUTPUT

1.5 V.F. AMP.

DIODE 2.5 DETECTOR

T13

456 KC. ALIGNING

6F7M

1.5 I.F. AMP.

456 KC. ALIGNING

6F7M

1.5 I.F. AMP.

456 KC. ALIGNING

T14

ANTENNAE
& GROUND
CONNECTIONS

MODEL "11/10P" (RADIO-PHONO)

TYPE 6R1031 CHASSIS

Rogers Alignment See "ROGERS MULTI-BAND AC & BATTERY RECEIVER ALIGNMENT"