

8Bit-Museum.de

DRAM memory comparison table for the "Retro Chip Tester Professional"

Identifier	Company	Test setting	Pro Rev.1+	Type	Size	Pins	RAS	CAS	Refresh Timing	RAS only	CBR	Hidden	Refresh	Remark
S4006	AMI	4008	adapter	1k x 1	1024	16	32 (AO-A4)	32 (AO-A4)	32, 2ms	x			AO-A4	Vss=10[5V], Vdd=9(-12V), requires adapter
MK4006	Mostek	4008	adapter	1k x 1	1024	16	32 (AO-A4)	32 (AO-A4)	32, 2ms	x			AO-A4	Vss=10[5V], Vdd=9(-12V), requires adapter
S4008	AMI	4008	adapter	1k x 1	1024	16	32 (AO-A4)	32 (AO-A4)	32, 2ms	x			AO-A4	Vss=10[5V], Vdd=9(-12V), requires adapter
MK4008	Mostek	4008	adapter	1k x 1	1024	16	32 (AO-A4)	32 (AO-A4)	32, 2ms	x			AO-A4	Vss=10[5V], Vdd=9(-12V), requires adapter
2104		2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
D2104A	Intel	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
4096	Fairchild	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
FM4027	Fairchild	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
M88227	Fujitsu	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
IM7027	Intersil	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
HM4027	Hitachi	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
TT4027	ITT	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
MK4015	Mostek	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 1ms	x			AO-A5	
MK4027	Mostek	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
MK4096	Mostek	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
MK4200	Mostek	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
MCM4027	Motorola	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
MCM4096	Motorola	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
MCM4604	Motorola	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
uPD14	NEC	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
M4015	SGS	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
M4027	SGS	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
2660	Signetics	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
4027	Signetics	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
4096	Signetics	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
TM54027	Texas Instruments	2104	X	4k x 1	4096	16	64 (AO-A5)	64 (AO-A5)	64, 2ms	x			AO-A5	
2107		2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter
Am9060	AMD	2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter
Am9107	AMD	2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter
D2107C	Intel	2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter
D2107B	Intel	2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter
8107B	Intel	2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter, untested
MM4280	National	2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter
MMS280	National	2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter
uPD111	NEC	2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter, untested
2580	Signetics	2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter, untested
TM54030	Texas Instruments	2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter, untested
TM54060	Texas Instruments	2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter
TMM414	Toshiba	2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter, untested
K565P1	(UdSSR)	2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter, untested
K56SRU1	(UdSSR)	2107	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5), requires adapter, untested
IM7505A	Intersil	6605	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5)
MCM6605	Motorola	6605	adapter	4k x 1	4096	22	4096 (AO-A11)		64, 2ms	x			AO-A5	22 Pin, CE=12V, Refresh (AO-A5)
Am9050	AMD	custom	adapter	4k x 1	4096	18	-	-	64, 2ms	x			AO-A5	Vbb=1, Vss=18, Vdd=10, CE=7, external definition
uPD418	NEC	custom	adapter	4k x 1	4096	18	-	-	64, 2ms	x			AO-A5	Vbb=1, Vss=18, Vdd=10, CE=7, external definition
TM54050	Texas Instruments	custom	adapter	4k x 1	4096	18	-	-	64, 2ms	x			AO-A5	Vbb=1, Vss=18, Vdd=10, CE=7, external definition
TM54051	Texas Instruments	custom	adapter	4k x 1	4096	18	-	-	64, 2ms	x			AO-A5	Vbb=1, Vss=18, Vdd=10, CE=7, external definition, untested
D2108-2-51573/1626	Intel	2108L	X	8k x 1	8192	16	64 (AO-A5)	128 (AO-A6)	128, 2ms	x			AO-A6	RAS A6=0
D2108-4-51572/1627	Intel	2108H	X	8k x 1	8192	16	64 (AO-A5)	128 (AO-A6)	128, 2ms	x			AO-A6	RAS A6=1
D2109-3-56001/6003	Intel	2108L	X	8k x 1	8192	16	64 (AO-A5)	128 (AO-A6)	128, 2ms	x			AO-A6	RAS A6=0
D2109-4-56000/6002	Intel	2108H	X	8k x 1	8192	16	64 (AO-A5)	128 (AO-A6)	128, 2ms	x			AO-A6	RAS A6=1
MMS298A	National	5298A	X	8k x 1	8192	16	128 (AO-A6)	128 (AO-A6)	128, 1ms	x			AO-A6	RAS A5=0
MMS298B	National	5298B	X	8k x 1	8192	16	128 (AO-A6)	64 (A1-A6)	128, 1ms	x			AO-A6	RAS A5=1, untested
TM54108-xxN10	Texas Instruments	4108-x0	X	8k x 1	8192	16	128 (AO-A6)	64 (A1-A6)	128, 2ms	x			AO-A6	CAS A0=0
TM54108-xxN11	Texas Instruments	4108-x1	X	8k x 1	8192	16	128 (AO-A6)	64 (A1-A6)	128, 2ms	x			AO-A6	CAS A0=1
MK4108-x0	Mostek	4108-x0	X	8k x 1	8192	16	128 (AO-A6)	64 (A1-A6)	128, 1ms	x			AO-A6	CAS A0=0
MK4108-x1	Mostek	4108-x1	X	8k x 1	8192	16	128 (AO-A6)	64 (A1-A6)	128, 1ms	x			AO-A6	CAS A0=1
MK4115-x0	Mostek	4108-x0	X	8k x 1	8192	16	128 (AO-A6)	64 (A1-A6)	128, 1ms	x			AO-A6	CAS A0=0
MK4115-x1	Mostek	4108-x1	X	8k x 1	8192	16	128 (AO-A6)	64 (A1-A6)	128, 1ms	x			AO-A6	CAS A0=1
4116		4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
Am9016	AMD	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
STC4116	EPSON	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
F16K	Fairchild	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
F4116	Fairchild	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
M88116	Fujitsu	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
M88126	Fujitsu	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
M88216	Fujitsu	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
HM4716	Hitachi	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
2116	Intel	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
2117	Intel	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
IM4116	Intersil	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
21-16935-01	ITT	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	DEC Part Number
ITT4116	ITT	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
MSK4116	Mitsubishi	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
MK4116	Mostek	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
MK4215	Mostek	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 1ms	x			AO-A6	
8041016A	Motorola	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
MCM4116	Motorola	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
MCM6616	Motorola	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
SCM90072	Motorola	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
MMS290	National	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
uPD2116	NEC	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
uPD416	NEC	4116	X	16k x 1	16384	16	128 (AO-A6)	128 (AO-A6)	128, 2ms	x			AO-A6	
NTE2117	NTE	4116	X	16k x 1	16384</									

Identifier	Company	Test setting	Pro Rev.1+	Type	Size	Pins	RAS	CAS	Refresh Timing	RAS only	CBR	Hidden	Refresh	Remark
M88281	Fujitsu	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	static column, untested
HM4864	Hitachi	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	
HYS164	Hyundai	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	256, 4ms	x	x	x	AD-A7	untested
HYS1C64	Hyundai	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	256, 4ms	x	x	x	AD-A7	untested
IMS2600	Immos	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	256, 4ms	x	x	x	AD-A7	
2164A	Intel	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	
2164B	Intel	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	
51C64	Intel	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	untested
51C65	Intel	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	static column, untested
C88164	Micro Elektronika	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	
MT4264	Micron	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	256, 4ms	x	x	x	AD-A7	
MSK4164ANP	Mitsubishi	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	
MK4564	Mostek	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	
MCM4164	Motorola	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	
MCM6665	Motorola	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
MCM3764	National	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	
MCM4164	National	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	256, 4ms	x	x	x	AD-A7	
uPD4164	NEC	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	
NTE4164	NTE	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	
MSM3764	OKI	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	
MN4164	Panasonic	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	
KM4164	Samsung	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
LM3364	Sanyo	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	
HY84164	Siemens	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	256, 4ms	x	x	x	AD-A7	
MH84164	TESLA	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	256, 4ms	x	x	x	AD-A7	
TMS4164	Texas Instruments	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	256, 4ms	x	x	x	AD-A7	
MK84563	Thomson	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
TMM4164	Toshiba	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
V51C64	Vitelco	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	256, 4ms	x	x	x	AD-A6	untested
K565P95	(UdSSR)	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
K565RU5	(UdSSR)	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
U2164	(DDR)	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
M88265	Fujitsu	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	Pin 1=RFSH, RFSH+HIGH is tested only
MK4164S	Mitsubishi	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A7	Pin 1=RFSH, RFSH+HIGH is tested only
MK4164	Mostek	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	Pin 1=RFSH, RFSH+HIGH is tested only
MCM6664	Motorola	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	Pin 1=RFSH, RFSH+HIGH is tested only
uPD4265	NEC	4164	X	64k x 1	65536	16	256 (A0-A7)	256 (A0-A7)	256, 4ms	x	x	x	AD-A7	Pin 1=RFSH, RFSH+HIGH is tested only
HM48128 (top)	Hitachi	41128 TOP	X	2x 64k x 1	131072	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
HM48128 (bottom)	Hitachi	41128 BOT	X	2x 64k x 1	131072	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
MT1128 (top)	Micron	41128 TOP	X	2x 64k x 1	131072	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
MT1128 (bottom)	Micron	41128 BOT	X	2x 64k x 1	131072	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
MK4128 (top)	Mostek	41128 TOP	X	2x 64k x 1	131072	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
MK4128 (bottom)	Mostek	41128 BOT	X	2x 64k x 1	131072	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
MSM37564 (top)	OKI	41128 TOP	X	2x 64k x 1	131072	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
MSM37564 (bottom)	OKI	41128 BOT	X	2x 64k x 1	131072	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
KM4128 (top)	Samsung	41128 TOP	X	2x 64k x 1	131072	16	256 (A0-A7)	256 (A0-A7)	256, 4ms	x	x	x	AD-A7	
KM4128 (bottom)	Samsung	41128 BOT	X	2x 64k x 1	131072	16	256 (A0-A7)	256 (A0-A7)	256, 4ms	x	x	x	AD-A7	
MS41128 (top)	Texas Instruments	41128 TOP	X	2x 64k x 1	131072	16	256 (A0-A7)	256 (A0-A7)	256, 4ms	x	x	x	AD-A7	
MS41128 (bottom)	Texas Instruments	41128 BOT	X	2x 64k x 1	131072	16	256 (A0-A7)	256 (A0-A7)	256, 4ms	x	x	x	AD-A7	
Z41250 (top)	Texas Instruments	41128 TOP	X	2x 64k x 1	131072	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
Z41250 (bottom)	Texas Instruments	41128 BOT	X	2x 64k x 1	131072	16	256 (A0-A7)	256 (A0-A7)	128, 2ms	x	x	x	AD-A6	
41256		41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
AS4C1259	ASI	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
M881256	Fujitsu	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
M881257	Fujitsu	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A8	nibble mode
M881C258	Fujitsu	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	static column, untested
GM71256	Goldstar	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
GM71C256A	Goldstar	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
HMS256-1	Hitachi	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
HMS1256	Hitachi	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
HMS1258	Hitachi	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 32ms	x	x	x	AD-A7	static column
HYS1C256	Hyundai	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	ripple mode, untested
HYS3C256	Hyundai	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
21256	Intel	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
51C256	Intel	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	ripple mode, untested
MT1256	Micron	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
MT1259	Micron	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
MSM4256	Mitsubishi	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
MCM6256	Motorola	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
MCM6257	Motorola	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	nibble mode
uPD41256	NEC	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
uPD41257	NEC	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	nibble mode
AAA2800	NMB Semiconductor	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	static column, untested
AAA2801	NMB Semiconductor	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	enhanced mode, untested
NTE1256	NTE	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
M41256	OKI	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
M41257	OKI	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	nibble mode
MSM41256	OKI	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
MSM41257	OKI	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	nibble mode
MSM51C256	OKI	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
MSM51C257	OKI	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	nibble mode
MN41256	Panasonic	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
KM41256	Samsung	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
KM41C256	Samsung	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
KM41257	Samsung	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	nibble mode
LH21256	Sharp	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
LM33256	Sanyo	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
HY841256	Siemens	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
SM4256	Texas Instruments	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
MS4256	Texas Instruments	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
TMS4257	Texas Instruments	41256	X	256k x 1	262144	16	512 (A0-A8)	512 (A0-A8)	256, 4ms	x	x	x	AD-A7	
TC51256	Toshiba	41256	X	256k x 1	2									

Identifier	Company	Test setting	Pro Rev.1+	Type	Size	Pins	RAS	CAS	Refresh Timing	RAS only	CBR	Hidden	Refresh	Remark
MSM4416	Mitsubishi	4416	X	16k x 4	65536	18	256 (AO-A7)	64 (A1-A6)	256, 4ms		x			AD-A7
UPD41416	NEC	4416	X	16k x 4	65536	18	256 (AO-A7)	64 (A1-A6)	256, 4ms		x			AD-A7
MN4264	Panasonic	4416	X	16k x 4	65536	18	256 (AO-A7)	64 (A1-A6)	256, 4ms		x			AD-A7
TMS4416	Texas Instruments	4416	X	16k x 4	65536	18	256 (AO-A7)	64 (A1-A6)	256, 4ms	x				AD-A7
4464		4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x	x		AD-A7
M8B1464	Fujitsu	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms	x	x	x		AD-A7
M8B1466	Fujitsu	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x	x		AD-A7
HMS50464	Hitachi	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms	x	x	x		AD-A7
HYS3C464	Hyundai	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms	x	x	x		AD-A7
P21464	Intel	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x			AD-A7
51C259H	Intel	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x	x		AD-A7
MT4067	Micron	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x	x		AD-A7
MSM4464	Mitsubishi	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x	x		AD-A7
uPD41464	NEC	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x	x		AD-A7
KM41464A	Samsung	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x	x		AD-A7
KM41466	Samsung	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x	x		AD-A7
LH2464	Sharp	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x	x		AD-A7
SM4464	Texas Instruments	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x			AD-A7
TMS4464	Texas Instruments	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x			AD-A7
TMM41464	Toshiba	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x	x		AD-A7
V53C464A	Vitellic	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x	x		AD-A7
UD61464	ZMD	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x	x		AD-A7
UD61466	ZMD	4464	X	64k x 4	262144	18	256 (AO-A7)	256 (AO-A7)	256, 4ms		x	x		AD-A7
44256		44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
AS4C4256	ASi	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
M8B51C4256A	Fujitsu	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
GM71C4256A	Goldstar	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
HMS14256	Hitachi	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
HYS34256	Hyundai	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
P21014	Intel	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
MT4C4256	Micron	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
MT4C4258	Micron	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
MSM444256	Mitsubishi	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
MSM444258	Mitsubishi	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
MCM514256	Motorola	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
uPD414256	NEC	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
uPD424256	NEC	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
uPD424258	NEC	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
uPD424266	NEC	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
uPD424268	NEC	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
AAA1M304	NMB Semiconductor	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
MSM514256A	OKI	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
KM44C256A	Samsung	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
LC34256	Sanyo	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
LH64256	Sharp	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
LH64258	Sharp	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
HYB514256B	Siemens	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
HYB534256B	Siemens	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
TMS44C256	Texas Instruments	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
TMS44C257	Texas Instruments	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
TC514256	Toshiba	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
V53C104	Vitellic	44256	X	256k x 4	1048576	20	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
AAA4M204	NMB Semiconductor	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
AAA4M205	NMB Semiconductor	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
M8B14400	Fujitsu	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
GM71C4400	Goldstar	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
HMS14400	Hitachi	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
HMS14410	Hitachi	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
HYS14400	Hyundai	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
MT4C4001	Micron	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
MSM44400	Mitsubishi	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
MCM514400	Motorola	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
uPD424400	NEC	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
MSM514400	OKI	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
KM44C1000	Samsung	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
HYB514400	Siemens	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
SM44400	Texas Instruments	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
TMS44400	Texas Instruments	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
HMS14400	Toshiba	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
TC514400	Toshiba	custom	external	1024k x 4	4194304	20	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
SIMM30 256k x 8	-	SIMM30 - 256k x 8	adapter	256k x 8	2097152	30	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
SIMM30 256k Parity	-	SIMM30-P - 256k x 1	adapter	256k x 1	262144	30	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
SIMM30 1024k x 8	-	SIMM30 - 1024k x 8	adapter	1024k x 8	8388608	30	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
SIMM30 1024k Parity	-	SIMM30-P - 1024k x 1	adapter	1024k x 1	1048576	30	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
SIMM40 4096k x 8	-	-	adapter	4096k x 8	33554432	30	2048 (AO-A10)	2048 (AO-A10)	2048, 16ms		x	x		AD-A10
SIMM30 4096k Parity	-	-	adapter	4096k x 1	4194304	30	2048 (AO-A10)	2048 (AO-A10)	2048, 16ms		x	x		AD-A10
SIMM30 IBM 256k x 8	-	SIMM30 - 256k x 8	adapter	256k x 8	2097152	30	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
SIMM30 IBM 256k Parity	-	SIMM30-P IBM - 256k x 1	adapter	256k x 1	262144	30	512 (AO-A8)	512 (AO-A8)	512, 8ms		x	x		AD-A8
SIMM30 IBM 1024k x 8	-	SIMM30 - 1024k x 8	adapter	1024k x 8	8388608	30	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
SIMM30 IBM 1024k Parity	-	SIMM30-P IBM - 1024k x 1	adapter	1024k x 1	1048576	30	1024 (AO-A9)	1024 (AO-A9)	1024, 16ms		x	x		AD-A9
ZIP16 64k x 1	-	custom	external	64k x 1	65536	16	256 (AO-A7)	256 (AO-A7)	256, 4ms		x	x		AD-A6
ZIP20 64k x 4	-	ZIP20 - 64k x 4	adapter	64k x 4	262144	20	256 (AO-A7)							