

LOUDSPEAKER REFERENCE LIST

Used in RCA VICTOR MODEL	Cone Diameter (Inches)	Voice Coil Impedance (Ohms at 400 C.P.S.)	Field Resistance D.C. Ohms	Speaker Stock Number
A-32, A-39, VR-52, VR-61	12	2.2	3300	S-2938
QU8	12	11.5	3000	37309
C10-1, C10-2, D10-1, D10-2, C12-1, C14-1	12	7.5	1800	9620
U-106, U-108, 810-K	12	2.2	1800	14535
A-8, 911K, 911KG, 911K-8	12	2.2	1800	31530
VR-8, VR-8A, VR-8L, VR-8S, VR-10, VR-10A, VR-10S	12	2.2	1800	31538
U-160, 916HF	12	11.5	1800	31718
D22-1	12	7.5	1700	9629
15K-1	12	12.0	1700	9719
812K	12	11.5	1700	14600
VR-62, VR-63	12	2.2	1630	S-3377
A-6, A-10	12	2.2	1300	S-2599
816K	12	11.5	1300	30131
C5-2, C5-3, C6-1, C6-2	12	2.2	1290	S-1563
98K	12	2.2	1290	S-2240
A-31, A-38	12	2.2	1290	S-2893
5K-1, 8K-1, 8U, 9K-1	12	2.2	1290	9696
86K, 87E, 87K, 88K, 97K, 98KS,	12	2.2	1290	14395
VR-2, A-4, VR-4, VR-6, VR-6A, U-70, 95K,				
96K, 97KG, 97K-1	12	2.2	1290	31592
A-2	12	2.2	1060	S-2459
A-30, A-34, A-36, A-36-A, A-37, VR-50,	12	2.2	1060	S-2827
A-33	12	11.5	1060	S-3029
VRA-45, VR-51, VR-58, VR-59, VR-59A, VR-60	12	2.2	1060	S-3036
C6-3, C6-4	12	2.2	1000	9622
QU8	12	11.5	900	37313
C7-1, D7-7, C8-15, C8-16, D8-1	12	2.2	845	9619
9U, 9U-2	12	2.2	700	9736
10K-1	12	3.3	700	9758
15U	12	12.0	336	9767
B-2, B-4, 6B2, 6B4	12	2.2	P.M.	S-2566
B-70	12	2.2	P.M.	S-2976
VR-62, VR-63	12	2.2	P.M.	36372
R-54, R-56, RE-81	10	4.0	2900 & 5900	See Note #1
R-49, 230, 331	10	4.0	8800	S-1507
140, 141, 340	10	4.0	6950	9438
R-22, R-22A	10	7.5	3000	See Note #2
280	10	4.0	2950	See Note #2
R-48, R-50, R-52	10	4.0	2250	See Note #2
RAE-84	10	7.5	2250	See Note #2
281	10	7.5	2060	9508
381	10	7.5	2060	9541
262	10	4.0	1975	9543
R-6, R-104, R-105, R-107, R0-112	10	7.5	1900	See Note #2
R-31, 210	10	4.0	1360	See Note #2
R-7, R-7A, R-8, R-8A, R-9, R-9A, R-15,				
R-16, RE-37	10	7.5	1330	9323
R-53, RE-80	10	4.0	1300	S-1300
R-35, R-39, RE-40, RE-57	10	10.0	1300	See Note #2
222	10	4.0	1290	9445
C5-1, 211, 214, 221, 224, 226, 321	10	4.0	1290	9527
242, 340A	10	4.0	1070	9536
R-21, RAE-59	10	10.0	900	See Note #2
R-20	10	7.5	900	See Note #2
R-12, RE-41, R109	10	7.5	860	See Note #2
R-90	10	4.0	860	See Note #2
86BK, 97BK, 97BK6	10	2.2	P.M.	S-1788
BC6-1, BC7-1, 235B	10	4.0	P.M.	7819
R-30	10	7.5	P.M.	9355
R-88	10	4.0	P.M.	9455
VR-44, VR-44A, VR-44C, R-97	9 x 6	4.5	1060	S-3231
R-32, R-34, RE-45, RE-46	8	10.0	2950	See Note #2
85K, 85KA, 88T, U-101, U-102, U-103	8	2.2	1300	14360
T6-1	8	2.2	1290	S-1567
R-95	8	2.2	1290	S-1696
5K-2, 5T-3, 5T-5, 5U, 8T-2, 9T-1	8	2.2	1290	9699
R96, R96A, R97E	8	2.2	1290	31453
143	8	3.0	1070	S-1484
T6-2	8	2.2	1000	9621
R-10	8	Magnetic	850	See Note #2
T7-1, T8-14	8	2.2	845	9618
BC4-1, BC4-2	8	Magnetic	460	S-1534
Commander (2nd Prod.)	8	3.0	4.0	S-3269
M-109	8	2.0	4.0	9596
Imperial	8	3.0	4.0	32987
85BK-1	8	2.2	P.M.	*S-1758
85BK, 85BT, 86BT	8	2.2	P.M.	*S-1776
95BK, 95BK-6, 95BT, 95BT-6	8	2.5	P.M.	S-2097
Commander	8	3.0	P.M.	S-2506
B-3, B-5, 6B3, 6B5	8	2.2	P.M.	S-2564
M-30	8	4.0	P.M.	8838
BT6-1, BT7-1, 135B	8	4.0	P.M.	9538

LOUDSPEAKER REFERENCE LIST

Used in RCA VICTOR MODEL	Cone Diameter (Inches)	Voice Coil Impedance (Ohms at 400 C.P.S.)	Field Resistance D.C. Ohms	Speaker Stock Number
P-31	8	3.0	P.M.	See Note #3
R-67, R-68	8	3.0	P.M.	See Note #3
67M-2	7.5	2.0	4.0	9774
T4-1	6	4.0	1800	S-1541
T4-2	6	4.0	1800	9630
85TA, 85T-2	6	3.6	1300	S-1825
95T-2, 96T, 97T-1	6	2.2	1300	S-2187
U-60, U-60A	6	2.2	1300	S-2281
A-22, A-22E, A-25, VR-42	6	3.4	1300	S-2875
VR-1, A-3, A-5	6	3.4	1300	33078
86T	6	3.6	1290	S-1821
118, 128, 129, AGR-136	6	4.0	1290	9514
122	6	4.0	1290	9449
T5-1, T5-2, 117, 119	6	4.0	1290	9586
97T	6	2.2	1290	#14613
A-24	6	3.4	1060	S-3293
Q-22, Q22-C	6	3.4	1060	35848
R-37	6	4.0	1060	See Note #2
BT4-1, BT4-2	6	Magnetic	460	S-1535
Clipper, (2nd Prod.)	6	3.4	4.0	S-3260
M-123	6	4.0	4.0	9491
M-104, M-108	6	3.0	4.0	9577
5M, 6M, 8M-1, 8M-3	6	3.0	4.0	9687
6M-2	6	3.0	4.0	9691
84BT-1	6	2.2	P.M.	S-1729
85BT-1	6	2.2	P.M.	# S-1757
94BT, 96BT	6	2.2	P.M.	S-2045
B-1	6	3.4	P.M.	S-2404
B-60	6	3.4	P.M.	S-2736
B-61, B-67	6	3.4	P.M.	S-2974
VR-41	6	3.4	P.M.	S-3003
Clipper	6	3.4	P.M.	S-3145
R-87	6	4.0	P.M.	9453
126B, 223B	6	4.0	P.M.	9502
Victorphone	5.5	3.0	P.M.	S-1908
84T-3	5	5.0	1800	S-1775
94T	5	5.0	1800	S-2085
Victorette	5	3.0	1800	S-2321
VR-3, Ace, Mascot, (Victorette 2nd Prod.)	5	3.0	1800	S-2388
A-23 (2nd Prod.)	5	3.4	1800	S-3246
R-101, R-106	5	4.0	1800	9467
A-20, A-20E	5	3.4	1800	32902
M-116	5	4.0	1500	See Note #2
R-28, R-29, RE-33, R-115	5	4.0	1360	See Note #2
5T-1	5	5.0	1290	S-1675
A-1	5	3.0	1060	S-2469
A-21	5	3.0	1060	S-2838
VR-40, Master Nipper, Master Nipper A	5	3.4	450	S-2777
67M	5	3.2	4.8	9772
8M, Royal	5	3.2	4.8	30781
8M, (2nd Prod.)	5	3.2	4.8	35464
Royal (2nd Prod.)	5	3.2	4.8	S-2416
M-34, M-105	5	4.0	4.4	See Note #2
B-62, B-64, 94BT-1, Companion	5	3.0	P.M.	S-2376
Duette	5	4.0	P.M.	S-2803
A-23	5	3.4	P.M.	S-3120
B-63	5	4.0	P.M.	S-3187
DUO	5	5.0	P.M.	S-3308
DUO (2nd Prod.)	5	5.0	P.M.	S-3373
94BT-1, Portette	5	3.0	P.M.	32162
Cruiser	5	2.2	P.M.	33394
96T-1	4	3.0	1290	31475
Nipperette-A	4	Magnetic	1205	S-3274
Little Nipper, Nipper	4	4.0	450	S-2429
Nipperette	4	3.5	P.M.	S-2753
Pick-Me-Up	4	3.0	P.M.	33058
BP-10, BP-10A	3	2.0	P.M.	36504

(*) 3 Types used - Supply description when ordering parts.

(#) 2 Types used - Supply description when ordering parts.

Note No. 1: Field composed of two separate windings.

Note No. 2: Complete speaker not available - See Model Service Notes for Parts.

Note No. 3: Use complete speaker Stock No. S-2506.