

# 8Bit-Museum.de

TTL/CMOS logic chips comparison table for the "Retro Chip Tester Professional"

Tests that have been verified with a real chip are highlighted in green.

Tests that have been reported to work but have not been verified yet are highlighted in yellow.

Tests marked in red have never been tested with a real chip but may work.

"RAM" or "ROM": use the corresponding entry in the main menu; "n/a": not available (in most cases it cannot be implemented); "TBD": to be done  
**Some of these ICs are marked with "(!)"**. Please refer the manual before testing this chip. "(\*)" means analog device, test result has limited informative value.

If you have some of the chips marked in yellow/red or not listed and do not need them, I would appreciate these to complete the tests.

"Setting" entry means that the IC is not available in the menu, you have to use the IC mentioned in this entry.

## Notes:

Fairchild 9xxxx = 74xxxx (e.g. 9LS54 = 74LS65); 93xxx = 74xxx (e.g. 93170 = 74170) test with 74xxx; CMOS: 14xxx = 40xxx (e.g. HD14193 = 40193) test with 40xxx  
 AMD Am25xxx = 74xxx (e.g. Am25LS158 = 74LS158, except listed); RFT D1xxx = 74xx, DLxxx = 74xxx (e.g. D172D = 7472, DL132D = 74132), MC8xx/9xx = SN158xx/9xx

Identifier	J	Pins	Status	UdSSR	UdSSR	DDR	Cyrillic	Philips	Siemens	Setting	Remark
7400	14	v15	KR1531LA3	K555LA3	DL000D	ЛА3	FJH131	FLH101			Quad 2-input NAND Gate
7401	14	v14		K555LA8		ЛА8	FJH231	FLH201			Quad 2-input NAND Gate with Open Collector Outputs
74H01	14	v19					GJH231				Quad 2-input NAND Gate with Open Collector Outputs
7402	14	v15	KR531LE1	K555LE1	DL002N	ЛЕ1	FJH221	FLH191			Quad 2-input NOR Gate
7403	14	v14		K555LA9	DL003D	ЛА9	FJH291	FLH291			Quad 2-input NAND Gate with Open Collector Outputs (different pinout than 7401)
7404	14	v15	KR1531LN1	K555LN1	DL004D	ЛН1	FJH241	FLH211			Hex Inverter
7405	14	v15	KR531LN2	K555LN2		ЛН2	FJH251	FLH271			Hex Inverter
7406	14	v14		K555LN3		ЛН3		FLH481			Hex Inverter
7407	14	v14		K555LP9		ЛП9		FLH491			Hex Buffer/Driver with 30V Open Collector Outputs
7408	14	v15	KR531LI1	K555LI1	DL008D	ЛИ1		FLH381			Quad 2-input AND Gate
7409	14	v13		K555LI2		ЛИ2		FLH391			Quad 2-input AND Gate with Open Collector Outputs
7410	14	v15	KR1531LA4	K555LA4	DL010D	ЛА4	FJH121	FLH111			Triple 3-input NAND Gate
7411	14	v14	KR531LI3	K555LI3	DL011D	ЛИ3		FLH581			Triple 3-input AND Gate
7412	14	v13	K155LA10	K555LA10		ЛА10		FLH501			Triple 3-input NAND Gate with Open Collector Outputs
7413	14	v15	K155TL1			ТЛ1	FJL131	FLH351			Dual Schmitt Trigger 4-input NAND Gate
7414	14	v14	K155TL2	K555TL2	DL014D	ТЛ2					Hex Schmitt Trigger Inverter
7415	14	v13		K555LI4		ЛИ4					Triple 3-input AND Gate with Open Collector Outputs
7416	14	v13	K155LN5			ЛН5		FLH481T			Hex Inverter
7417	14	v14	K155LN4			ЛН4		FLH491T			Hex Buffer/Driver with 15V Open Collector Outputs
7418	14	v13									Dual 4-input NAND Schmidt Trigger
7419	14	v14					FJH401				Hex Schmitt Trigger Inverter
7420	14	v14	KR1531LA1	K555LA1	DL020D	ЛА1	FJH111	FLH121			Dual 4-input NAND Gate
7421	14	v15		K555LI6	DL021D	ЛИ6					Dual 4-input AND Gate
7422	14	v13	K155LA7	K555LA7		ЛА7		FLH611			Dual 4-input NAND Gate with Open Collector Outputs
7423	16	v15	K155LE2			ЛЕ2		FLH511			Expandable Dual 4-input NOR Gate with Strobe
7424	14	v16									Quad 2-input NAND Gate
7425	14	v15	K155LE3			ЛЕ3		FLH521			Dual 4-input NOR Gate with Strobe
7426	14	v15	K155LA11		D126D	ЛА11	FJH301	FLH291U			Quad 2-input NAND Gate with 15V Open Collector Outputs
7427	14	v15	K155LE4	K555LE4		ЛЕ4		FLH621			Triple 3-input NOR Gate
7428	14	v15		K555LE5		ЛЕ5		FLH661			Quad 2-input NOR Gate Buffer
7430	14	v14	KR531LA2	K555LA2	DL030D	ЛА2	FJH101	FLH131			8-input NAND Gate
7431	16	v13									Hex Delay Elements
7432	14	v14	K155LL1	K555LL1	DL032D	ЛЛ1		FLH631			Quad 2-input OR Gate
7433	14	v15		K555LE11		ЛЕ11					Quad 2-input NOR Gate Buffer with Open Collector Outputs
7434	14	v13		K555LI9		ЛИ9					Hex Buffer
7435	14	v13	K555IM7			ИМ7					Hex Buffer, Open Collector
7436	14	v13									Quad 2-input NOR Gate (different pinout than 7402)
7437	14	v13		K555LA12	DL037D	ЛА12		FLH531			Quad 2-input NAND Gate
7438	14	v14		K555LA13	DL038D	ЛА13		FLH541			Quad 2-input NAND Gate with Open Collector Outputs
7439	14	v13									Quad 2-input NAND Gate
7440	14	v14		K555LA6	DL040D	ЛА6	FJH141	FLH141			Dual 4-input NAND Gate
7441	16	v16									BCD to Decimal Decoder / Nixie tube Driver (insert at position 4)
7442	16	v14		K555ID6		ИД6	FJH261	FLH281			Binary-Coded Decimal
7443	16	v16						FLH361			Excess-3 to Decimal Decoder
7444	16	v16						FLH371			Excess-3-Gray to Decimal Decoder
7445	16	v16		K555ID24		ИД24		FLH111			BCD to Decimal Decoder/Driver
7446	16	v15			D146D			FLL121U			BCD to 7-segment Decoder/Driver
7447	16	v15			D147D			FLL121T			BCD to 7-segment Decoder/Driver ("6" and "9" without tail, a few 7447 have a tail, use 74247 instead)
7448	16	v15						FLH551			BCD to 7-segment Decoder/Driver
7449	14	v15									BCD to 7-segment Decoder/Driver
7450	14	v16	K131LR1		D150D	ЛР1	FJH151	FLH151			Dual 2-Wide 2-input AND-OR-INVERT Gate
7451	14	v15			D151D		FJH161	FLH161			Dual 2-Wide 2-input AND-OR-INVERT Gate (51, H51, S51 only)
74LS51	14	v15		K555LR11	DL051D	ЛР11					Dual 2-3-3-input AND-OR-INVERT Gate (L51, LS51, ...)
7452	14	v18									Expandable 4-Wide 2-input AND-OR Gate
7453	14	v15	K131LR3		D153D	ЛР3	FJH171	FLH171			Expandable 2-2-2-2-input AND-OR-INVERT Gate (53 only)
74H53	14	v13									Expandable 2-2-2-3-input AND-OR-INVERT Gate (H53 only)
7454	14	v15			D154D		FJH181	FLH181			2-2-2-2-input AND-OR-INVERT Gate (54 only)
74H54	14	v15					GJH181				2-2-2-3-input AND-OR-INVERT Gate (H54 only)
74LS54	14	v14		K555LR13		ЛР13					2-2-3-3-input AND-OR-INVERT Gate (L54, LS54, ...)
74H55	14	v13									2-Wide 4-input AND-OR-INVERT Gate (H55 only)
74LS55	14	v13									2-Wide 4-input AND-OR-INVERT Gate (L55, LS55, ...)
7456	8	v23									50:1 frequency Divider (insert at position 7)
7457	8	v23									60:1 frequency Divider (insert at position 7)
7458	14	v13									2-wide 2-input and 2-wide 3-input AND-OR Gates
7460	14	v16	K155LD1		D160D	ЛД1	FJY101	FLY101			Dual 4-input expander
7461	14	v13									Triple 3-input Expander
7462	14	v17									3-2-2-3-input Expander
7463	14	n/a									Hex current sensing interface Gates
7464	14	v16		K555LR9		ЛР9					4-3-2-2 input AND-OR-Invert Gate
7465	14	v16	KR531LR10			ЛР10					4-3-2-2 input AND-OR-INVERT Gate with Open Collector Output
7468	16	v16									Dual 4-Bit Decade Counters (LS68, not L68)
7469	16	v16									Dual 4-Bit Binary Counters (LS69, not L69)
7470	14	v15					FJJ101	FJY101			AND Gated J-K Master-Slave Flip-Flop, asynchronous Preset and Clear
74H71	14	v17									AND-OR-gated J-K Master-Slave Flip-Flop, Preset (H71 only)
74L71	14	v13									AND-OR-gated R-S Master-Slave Flip-Flop, Preset and Clear (L71 only)
7472	14	v15		K155TV1		D172D	TB1	FJJ111	FJY111		AND Gated J-K Master-Slave Flip-Flop, asynchronous Preset and Clear
7473	14	v14					FJJ121	FJY121			Dual J-K Flip-Flop Flip-Flop with Clear (insert at position 5)
7474	14	v14	K131TM2	K555TM2	DL074D	ТМ2	FJJ131	FJY141			Dual D Positive Edge triggered Flip-Flop with Preset and Clear
7475	16	v14		K555TM7	D175D	ТМ7	FJJ181	FJY151			4-bit Bistable Latch, complementary Outputs (insert at position 4)
7476	16	v18					FJJ191	FJY131			Dual J-K Flip-Flop with Preset and Clear (insert at position 5)
74LS76	16	v22									Dual J-K Flip-Flop with Preset and Clear, negative triggered (insert at position 5)
7477	16	v14		SN74LS77		ТМ5					4-Bit Bistable Latch (insert at position 5)
74H78	14	v13									Dual J-K Flip-Flop, Preset, Common Clock and Common Clear, positive Clock (H78 only)
74L78	14	v13									Dual J-K Flip-Flop, Preset, Common Clock and Common Clear, positive Clock (L78 only) (insert at position 5)
74LS78	14	v15									Dual J-K Flip-Flop, Preset, Common Clock and Common Clear, negative Clock (LS78, ...) (insert at position 5)
7479	14	v16									Dual D positive edge triggered Flip-Flop, asynchronous Preset and Clear
7480	14	v16	K155IM1			ИМ1	FJH191	FLH221			Gated Full Adder

Identifier	J	Pins	Status	UdSSR	UdSSR	DDR	Cyrillic	Phillips	Siemens	Setting	Remark
7481	14	RAM		K155RU1		D181D	PY1		FLQ111		16-bit RAM (4 x 4)
7482	14	v16		K155IM2			IM2	FJH201	FLH231		2-bit Binary Full Adder (insert at position 5)
7483	16	v15		K155IM3	K555IM3		IM3	FJH211	FLH241		4-bit Binary Full Adder (insert at position 4)
7484	16	RAM		K155RU3			PY3		FLQ121		16-bit RAM (4 x 4)
7485	16	v14		KR531SP1	K555SP1		CP1		FLH431		4-bit Magnitude Comparator
74C85	16	v17									4-bit Magnitude Comparator
7486	14	v14		KR531LP5	K555LP5	DL086D	ЛП5	FJH271	FLH341		Quad 2-input XOR Gate
74L86	14	v18									Quad 2-input XOR Gate
7487	14	v15							FLH441		4-bit true/complement/zero/one Element
7488	16	ROM						FJQ101	FLR101		256-bit ROM (32x8)
7489	16	RAM						FJQ111	FLQ101		64-bit RAM (16x4), inverted Outputs
7490	14	v14 (I)		K555IE2		DL090D	IE2	FJJ141	FUJ161		4-bit Decade Counter (insert at position 4)
74C90	14	v14 (I)								7490	4-bit Decade Counter (insert at position 4)
7491	14	v17		K134IR2		D191D	IP2	FJJ151	FUJ221		8-bit Shift Register, serial in, serial out, Gated input (insert at position 4)
7492	14	v15 (I)		K155IE4			IE4	FJJ251	FUJ171		Divide-by-12 Counter (insert at position 4)
7493	14	v14 (I)			K555IE5	DL093D	IE5	FJJ211	FUJ181		4-bit Binary Counter (insert at position 4)
74C93	14	v17									4-bit Binary Counter (insert at position 5)
74L93	14	v22									4-bit Binary Counter (insert at position 5)
7494	16	v17							FUJ231		4-bit Shift Register, Dual asynchronous Presets (insert at position 4)
74C95	14	v18									4-bit Shift Register (insert at position 5)
74L95	14	v15									4-bit Shift Register (insert at position 5)
7495	14	v14			K555IR1	D195D	IP1	FJJ231	FUJ191		4-bit Shift Register (insert at position 5)
7496	16	v18						FJJ241	FUJ261		5-bit parallel-in/parallel-out Shift Register, asynchronous Preset (insert at position 4)
7497	16	v17		K155IE8			IE8		FUJ331		synchronous 6-bit Binary rate Multiplier
7498	16	v15		K134IR5			IP5				4-bit Data Selector/storage Register
7499	16	v24									4-bit bidirectional universal Shift Register (insert at position 5)
74100	24	v18							FUJ301		Dual 4-bit bistable Latch
74101	14	v13									AND-OR-gated J-K negative-edge-triggered Flip-Flop, Preset
74102	14	v13									AND-gated J-K negative-edge-triggered Flip-Flop, Preset and Clear
74103	14	v15									Dual J-K negative-edge-triggered Flip-Flop, Clear (insert at position 5)
74104	14	v15							FUJ281		J-K Master-Slave Flip-Flop
74105	14	v15							FUJ291		J-K Master-Slave Flip-Flop, J2 and K2 inverted
74106	16	v13									Dual J-K negative-edge-triggered Flip-Flop, Preset and Clear (insert at position 5)
74107	14	v24									Dual J-K Flip-Flop with Clear
74L5107	14	v14			K555TV6		ТВ6	FJJ261	FUJ271		Dual J-K negative-edge-triggered Flip-Flop with Clear (LS107, HC107)
74108	14	v13									Dual J-K negative-edge-triggered Flip-Flop, Preset, common Clear and common Clock
74109	16	v15		K155TV15			ТВ15				Dual J-Not-K Positive-Edge-triggered Flip-Flop with Clear and Preset
74110	14	v15							FUJ341		AND-gated J-K Master-Slave Flip-Flop, Data lockout
74111	16	v16							FUJ351		Dual J-K Flip-Flop with Preset and Clear
74112	16	v15			K555TV9	DL112D	ТВ9				Dual J-K Negative-Edge-triggered Flip-Flop with Clear and Preset
74113	14	v15		KR531TV10			ТВ10				Dual J-K Negative-Edge-triggered Flip-Flop with Preset
74114	14	v16		KR531TV11			ТВ11				Dual J-K Negative-Edge-triggered Flip-Flop with Preset
74115	14	v17							FUJ521		Dual J-K Flip-Flop Flip-Flop with Clear
74116	24	v15									Dual 4-bit Latch, Clear
74117	24	TBD									AND-Gated J-K Flip-Flop, one J and K input inverted
74118	16	v15 (I)						FJJ291	FUJ361		Hex Set/Reset Latch, common reset
74119	24	v21						FJJ301	FLJ371		hex Set/Reset Latch
74120	14	v17							FLY181		Dual pulse synchronizer/Drivers
74121	14	v22		K155AG1		D121D	АГ1	FJK101	FLK101		monostable Multivibrator (adapter required)
74122	14	v22							FLK111		retriggerable monostable Multivibrator, Clear (adapter required)
74123	16	v22			K533AG3	DL123D	АГ3		FLK121		Dual retriggerable monostable Multivibrator, Clear (adapter required)
74124	16	n/a		KR531GG1			ГГ1				Dual voltage-controlled Oscillator
74125	14	v14		K155LP8	K555LP8		ЛП8				Quad Bus Buffer with Three-State Outputs
74126	14	v14			K555LP14		ЛП14				Quad Bus Buffer with Three-State Outputs
74128	14	v15		K155LE6			ЛЕ6				Quad 2-input NOR Gate
74130	16	v22									Retriggerable monostable Multivibrator (adapter required)
74131	16	v16									Quad 2-input AND Gate
74132	14	v14		KR531TL3		DL132D	ТЛ3		FLH601		Quad 2-input NAND Gate
74133	16	v13									13-input NAND Gate
74134	16	v13		KR531LA19			ЛА19				12-input NAND
74135	16	v13									XOR/NOR Gate
74136	14	v15			K555LP12		ЛП12				Quad 2-input Exclusive OR with Open Collector Outputs
74137	16	v15									3 to 8-line Decoder/Demultiplexer with Address Latch
74138	16	v14		KR531ID7	K555ID7		ИД7				3 to 8-line Decoder/Demultiplexer
74139	16	v14		KR531ID14			ИД14				Dual 2 to 4-line Decoder/Demultiplexer
74140	14	v13		KR531LA16			ЛА16				Dual 4-input NAND Gate
74141	16	v14		K155ID1			ИД1	FJL151	FLL101		BCD to Decimal Decoder/Driver for cold-cathode indicator / Nixie tube (insert at position 4)
74142	16	v22							FLL151		Decade Counter/Latch/decoder/Driver for Nixie tubes
74143	24	v18							FLJ171		Decade Counter/Latch/decoder/7-segment Driver
74144	24	v18							FLL171T		Decade Counter/Latch/decoder/7-segment Driver
74145	16	v14			K555ID10		ИД10		FLL111T		BCD to Decimal Decoder/Driver
74146	14	TBD									3-line to 8-line Decoder
74147	16	v14			K555IV3		ИВ3				10-Line to 4-Line Priority Encoder
74148	16	v14			K555IV1		ИВ1				8-Line to 3-Line Priority Encoder
74149	20	v13									8-line to 8-line priority encoder
74150	24	v14			K555KP1		КП1		FLY111		16-line to 1-line Data Selector/Multiplexer
74151	16	v14		KR531KP7	K555KP7		КП7		FLY121		8-line to 1-line Data Selector/Multiplexer
74152	14	v13		K155KP5			КП5				8-line to 1-line Data Selector/Multiplexer, inverting Output
74153	16	v14		KR531KP2	K555KP2		КП2		FLY131		Dual 4-Line to 1-Line Data Selector/Multiplexer
74154	24	v14			K555ID3		ИД3	FJH341	FLY141		4-Line to 16-Line Decoder/Demultiplexer
74155	16	v14			K555ID4	DL155D	ИД4	FJH491	FLY151		Dual 2-Line to 4-Line Decoder/Demultiplexer
74156	16	v15			K555ID5		ИД5		FLY161		Dual 2-Line to 4-Line Decoder/Demultiplexer with Open Collector Outputs
74157	16	v14			K555KP16		КП16		FLY171		Quad 2-Line to 1-Line Data Selector/Multiplexer
74158	16	v15			K555KP18		КП18				Quad 2-Line to 1-Line Data Selector/Multiplexer
74159	24	v15									4-Line to 16-Line Decoder/Demultiplexer, Open Collector
74160	16	v19		K155IE9			IE9		FUJ401		Synchronous 4-bit Decade Counter with asynchronous Clear
74161	16	v19		KR531IE10	K555IE10		IE10		FUJ411		Synchronous 4-bit Binary Counter with asynchronous Clear
74162	16	v19			K555IE11		IE11		FUJ421		Synchronous 4-bit Decade Counter with synchronous Clear
74163	16	v19			K555IE18		IE18		FUJ431		Synchronous 4-bit Binary Counter with synchronous Clear
74164	14	v14			K555IR8	DL164D	IP8		FUJ441		8-bit Parallel-Out Serial Shift Register with asynchronous Clear
74165	16	v15			K555IR9		IP9		FUJ451		8-bit Serial Shift Register
74166	16	v14			K555IR10		IP10		FUJ461		8-bit Shift Register Register
74167	16	v22							FUJ471		Synchronous decade rate Multiplier
74168	16	v16		KR531IE16			IE16				Synchronous Presettable 4-bit Up/Down decade Counter
74169	16	v16		KR531IE17			IE17				Synchronous Presettable 4-bit Up/Down Binary Counter
74170	16	RAM		K155RP1	K555IR32		IP32	FJQ101	FLQ131		4 by 4 Register File with Open Collector Outputs
74171	16	v18									Quad D Flip-Flops with Clear
74172	24	v18									16-bit multiple Port Register file (8x2), comprehensive test using Port 2 by SRAM testing
74173	16	v14		K155IR15	K555IR15		IP15				Quad D Flip-Flop with Three-State Outputs
74174	16	v14		KR531TM9	K555TM9		ТМ9		FUJ531		Hex D Flip-Flop with Common Clear
74175	16	v14		KR531TM8	K555TM8	DL175D	ТМ8		FUJ541		Quad D Edge-triggered Flip-Flop with Complementary Outputs and asynchronous Clear
74176	14	v16									Presettable decade (bi-quinary) Counter/Latch
74177	14	v16									Presettable Binary Counter/Latch
74178	14	v17									4-bit parallel-access Shift Register

Identifier	J	Pins	Status	UdSSR	UdSSR	DDR	Cyrillic	Philips	Siemens	Setting	Remark
74179	16	v17									4-bit parallel-access Shift Register, asynchronous Clear input, complementary Qd Output
74180	14	v14			K555IP2		ИП2	FJH281	FLH421		9-bit odd/even parity bit generator and checker
74181	24	v13		KR531IP3	K555IP3		ИП3	FJH451	FLH401		4-Bit Arithmetic Logic Unit and Function Generator
74182	16	v13		K155IP4			ИП4		FLH411		Lookahead Carry Generator
74183	14	v15			K555IM5		ИМ5		FLH451		Dual carry-save Full Adder
74184	16	v16		K155PR6			ПР6		FLH561		BCD to Binary converter
74185	16	v15		K155PR7			ПР7		FLH571		6-bit Binary to BCD converter (->check also with 7488 ROM)
74186	24	ROM									512-bit ROM (64x8)
74187	16	ROM							FLR111		1024-bit ROM (256x4)
74188	16	ROM							FLR121		256-bit PROM (32x8)
74189	16	RAM		KR531RU8			PY8				64-bit RAM (16x4), inverting Outputs
74190	16	v14			K555IE12		ИЕ12		FLJ201		Synchronous Up/Down Decade Counter
74191	16	v15			K555IE13		ИЕ13		FLJ211		Synchronous Up/Down Binary Counter
74192	16	v28			K555IE6	DL192D	ИЕ6		FLJ241		Synchronous Up/Down Decade Counter with Clear
74193	16	v28			K555IE7	DL193D	ИЕ7	FJJ411	FLJ251		Synchronous Up/Down Binary Counter with Clear
74194	16	v14		KR531IR11	K555IR11A	DL194D	ИР11		FLJ551		4-Bit Bidirectional Universal Shift Register
74195	16	v14		KR531IR12			ИР12		FLJ561		4-Bit Parallel-Access Shift Register
74196	14	v15		KR531IE14	K555IE14		ИЕ14		FLJ381		4-bit decade Counter
74197	14	v16		KR531IE15	K555IE15		ИЕ15		FLJ391		4-bit Binary Counter
74198	24	v18		K155IR13			ИР13		FLJ311		8-bit bidirectional universal Shift Register
74199	24	v18							FLJ321		8-bit universal Shift Register, J-Not-K serial inputs
74200	16	RAM							FLQ141		256-bit RAM (256x1)
74201	16	RAM									256-bit RAM (256x1)
74206	16	RAM									256-bit RAM (256x1)
74207	16	RAM									1024-bit RAM (256x4)
74208	20	RAM									1024-bit RAM (256x4), separate Data In- and Outputs
74209	16	RAM									1024-bit RAM (1024x1)
74210	20	v28									Octal Buffer, inverting
74211	20	RAM									144-bit RAM (16x9) with Output Latch
74212	20	RAM									144-bit RAM (16x9)
74213	20	RAM									192-bit RAM (16x12)
74214	16	RAM									1024-bit RAM (1024x1)
74215	16	RAM									1024-bit RAM (1024x1) with power-down mode
74216	16	RAM									1024-bit RAM (1024x1) with power-down mode
74217	20	RAM									1024-bit RAM (1024x1) with power-down mode
74218	20	RAM									1024-bit RAM (1024x1) with power-down mode
74219	20	FIFO									64-bit RAM (16x4), non-inverting Outputs
74221	16	v22		K555AG4	K555AG4		АГ4				Dual monostable Multivibrator (adapter required)
74222	20	FIFO									64-bit FIFO memory (16x4), synchronous, input/Output ready enable
74224	16	FIFO									64-bit FIFO memory (16x4), synchronous
74225	16	FIFO		KR531RU10			PY10				80-bit FIFO memory (16x5), asynchronous
74226	16	TBD									4-bit parallel latched Bus Transceiver
74227	20	FIFO									64-bit FIFO memory (16x4), synchronous, input/Output ready enable
74228	16	FIFO									64-bit FIFO memory (16x4), synchronous
74229	20	FIFO									80-bit FIFO memory (16x5), asynchronous
74230	20	v19									Dual 4-bit Buffer/Driver, one inverted, one non-inverted; negative enable
74231	20	v19									Dual 4-bit Buffer/Driver, both inverted; one positive and one negative enable
74232	16	FIFO									64-bit FIFO memory (16x4), asynchronous
74233	20	FIFO									80-bit FIFO memory (16x5), asynchronous
74234	16	FIFO									256-bit FIFO memory (64x4), asynchronous
74235	20	FIFO									320-bit FIFO memory (64x5), asynchronous
74236	16	FIFO									256-bit FIFO memory (64x4), asynchronous
74237	16	v13									3-of-8 Decoder/Demultiplexer with Address Latch
74238	16	v15									3-of-8 Decoder/Demultiplexer
74239	16	TBD									Dual 2-of-4 Decoder/Demultiplexer, Active High Outputs
74240	20	v15		KR531AP3	K555AP3		АП3				Octal Buffer, inverting Outputs
74241	20	v15		KR531AP4	K555AP4		АП4				Octal Buffer, non-inverting Outputs
74242	14	v13			K555IP6		ИП6				Quad Bus Transceiver with inverted Three-State Outputs
74243	14	v15			K555IP7		ИП7				Quad Bus Transceiver with non-inverted Three-State Outputs
74244	20	v14			K555AP5		АП5				Octal Buffer with non-inverted Three-State Outputs
74245	20	v14			K555AP6		АП6				Octal Bus Transceiver with non-inverted Three-State Outputs
74246	16	v15									BCD to 7-segment Decoder/Driver
74247	16	v15			K555ID18	D347D	ИД18				BCD to 7-segment Decoder/Driver
74248	16	v15				D348D					BCD to 7-segment Decoder/Driver
74249	16	v15									BCD to 7-segment Decoder/Driver
74250	24	TBD									1-of-16 Data Selector/Multiplexer
74251	16	v14		KR531KP15	K555KP15	DL251D	КП15				8-line to 1-line Data Selector/Multiplexer with Three-State Outputs
74253	16	v15		KR531KP12	K555KP12	DL253D	КП12				Dual 4-line to 1-line Data Selector/Multiplexer with Three-State Outputs
74255	16	v28									Dual 2-line to 4-line Decoder/Demultiplexer, Inverting Three-State Outputs
74256	16	v18									Dual 4-bit addressable Latch
74257	16	v14		KR531KP11	K555KP11	DL257D	КП11				Quad 2-line to 1-line Data Selector/Multiplexer with non-inverted Three-Outputs (= MOS 7708)
74258	16	v15		KR531KP14	K555KP14		КП14				Quad 2-line to 1-line Data Selector/Multiplexer with inverted Three-State Outputs (= MOS 7709)
74259	16	v14			K555IR30	DL259D	ИР30				8-bit addressable Latch (also JM38510/65402BEA)
74260	14	v15		KR531LE7			ЛЕ7				Dual 5-input NOR Gate
74261	16	v17			K555IP8		ИП8				2-bit by 4-bit parallel Binary Multiplier
74262	20	ROM									5760-bit ROM (Teletext character Set, 128 characters 5x9)
74264	16	TBD									Look Ahead Carry Generator
74265	16	v16									Quad complementary Output Elements
74266	14	v13			K555LP13		ЛП13				Quad 2-input Exclusive NOR Gate with Open Collector Outputs
74268	16	TBD									Hex D-Type Latches, Common Output Control, Common Enable
74269	24	v18									8-bit bidirectional Binary Counter
74270	16	ROM									2048-bit ROM (512x4)
74271	20	ROM									2048-bit ROM (256x8)
74273	20	v15			K555IR35		ИР35				8-bit Register, asynchronous Clear
74274	20	TBD									4-bit by 4-bit Binary Multiplier
74275	16	v22									7-bit slice Wallace tree
74276	20	v18									Quad J-Not-K edge-triggered Flip-Flops, separate Clocks, common Preset and Clear
74278	14	v13									4-bit cascadeable priority Registers, latched Data inputs
74279	16	v16			K555TR2		ТР2				Quad Set-reset Latch
74280	14	v14		KR531IP5	K555IP5		ИП5				9-Bit Odd/Even Parity Generator/Checker
74281	24	TBD									4-bit parallel Binary Accumulator
74282	20	TBD									Look-Ahead Carry Generator, Selectable Carry inputs
74283	16	v15			K555IM6		ИМ6				4-Bit Binary Full Adder
74284	16	v16									4-bit by 4-bit parallel Binary Multiplier (low order 4 bits of product)
74285	16	v16									4-bit by 4-bit parallel Binary Multiplier (high order 4 bits of product)
74286	14	v17									9-bit parity generator/checker, bus Driver parity I/O Port
74287	16	ROM									1024-bit PROM (256x4)
74288	16	ROM									256-bit PROM (32x8)
74289	16	RAM		KR531RU9			PY9				64-bit RAM (16x4), inverted Outputs
74290	14	v16		K555IE20			ИЕ20				decade Counter (separate divide-by-2 and divide-by-5 sections)
74292	16	v16									Programmable Frequency Divider/Digital Timer
74293	14	v13									4-Bit Binary Counter
74294	16	v25									Programmable Frequency Divider/Digital Timer
74295	14	v16			K555IR16	DL295D	ИР16				4-bit bidirectional Shift Register

Identifier	J	Pins	Status	UdSSR	UdSSR	DDR	Cyrillic	Phillips	Siemens	Setting	Remark
74297		16	n/a								digital phase-locked loop filter
74298		16	v13		K555KP13		КП13				Quad 2-input Multiplexer with Storage
74299		20	v14	KR531R24		DI299D	ИР24				8-Bit Bidirectional Universal Shift/Storage Register with Three-State Outputs
74300		16	RAM								256-bit RAM (256x1)
74301		16	RAM								256-bit RAM (256x1)
74302		16	RAM								256-bit RAM (256x1)
74309		16	RAM								1024-bit RAM (1024x1)
74310		20	v28								Octal Buffer, Inverting
74311		20	RAM								144-bit RAM (16x9) with Output Latch
74312		20	RAM								144-bit RAM (16x9)
74313		20	RAM								192-bit RAM (16x12)
74314		16	RAM								1024-bit RAM (1024x1)
74315		16	RAM								1024-bit RAM (1024x1) with power-down mode
74316		16	RAM								1024-bit RAM (1024x1) with power-down mode
74317		20	RAM								1024-bit RAM (1024x1) with power-down mode
74318		20	RAM								1024-bit RAM (1024x1) with power-down mode
74322		20	v17		K555IR28		ИР28				8-Bit Shift Register, Sign Extend
74323		20	v16	KR531R29			ИР29				8-bit Bidirectional Universal Shift/Storage Register, synchronous Clear
74340		20	v28								Octal Buffer, inverting Outputs
74341		20	v28								Octal Buffer, non-inverting Outputs
74344		20	v28								Octal Buffer with non-inverted Three-State Outputs
74347		16	v16								BCD-to-7 segment Decoders/Drivers, low voltage version of 7447
74348		16	v13		K555IV2		ИВ2				8 to 3-line priority encoder
74350		16	v18		KP1531R42		ИР42				4-bit Shifter
74351		20	v18								Dual 8-line to 1-line Data Selectors/Multiplexers, 4 common Data inputs
74352		16	v16		K555KP19		КП19				Dual 4-line to 1-line Data Selectors/Multiplexers, inverting Outputs
74353		16	v21		K555KP17		КП17				Dual 4-line to 1-line Data Selectors/Multiplexers, inverting Outputs
74354		20	v13								8-line to 1-line Data Selector/Multiplexer, transparent Registers
74355		20	v13								8-line to 1-line Data Selector/Multiplexer, transparent Registers
74356		20	v13								8-line to 1-line Data Selector/Multiplexer, edge-triggered Registers
74357		20	v19								8-line to 1-line Data Selector/Multiplexer, edge-triggered Registers
74363		20	v13								Octal transparent Latch
74364		20	v13								Octal edge-triggered D-Type Register
74365		16	v15	K155LP10			ЛП10				Hex Buffer with non-inverted Three-State Outputs
74366		16	v15	K155LN6			ЛН6				Hex Buffer with inverted Three-State Outputs
74367		16	v14	K155LP11			ЛП11				Hex Buffer with non-inverted Three-State Outputs
74368		16	v15		K555LN7		ЛН7				Hex Buffer with inverted Three-State Outputs
74370		16	ROM								2048-bit ROM (512x4)
74371		20	ROM								2048-bit ROM (256x8)
74373		20	v14	KR531R22	K555IR22		ИР22				Octal Register with Three-State Outputs
74374		20	v14	KR531R23	K555IR23	DL374D	ИР23				Octal Register with Three-State Outputs
74375		16	v15		K555TM10		ТМ10				Quad Bistable Latch
74376		16	v16								Quad J-Not-K Flip-Flop, common Clock and common Clear
74377		20	v14		K555IR27		ИР27				8-Bit Register with Clock Enable
74378		16	v16								6-Bit Register with Clock Enable
74379		16	v16								4-bit Register, Clock enable and complementary Outputs
74380		24	TBD								8-bit multifunction Register
74381		20	v27	KR531IK2			ИК2				4-bit arithmetic Logic Unit/Function Generator, generate and propagate Outputs
74F381		20	v18								4-bit arithmetic Logic Unit/Function Generator, generate and propagate Outputs
74382		20	v27								4-bit arithmetic Logic Unit/Function Generator, ripple carry and overflow Outputs
74F382		20	v18								4-bit arithmetic Logic Unit/Function Generator, ripple carry and overflow Outputs
74384		16	v22		K555IP9		ИП9				8-bit by 1-bit two's complement Multipliers
74385		20	v18								Quad serial Adder/Subtractor
74386		14	v13								Quad 2-input Exclusive-OR Gate
74387		16	ROM								1024-bit PROM (256x4)
74388		16	v24								4-bit D-Type Register
74390		16	v15								Dual 4-Bit Decade Counter
74393		14	v15		K555IE19		ИЕ19				Dual 4-Bit Binary Counter
74395		16	v16		K555IR25		ИР25				4-bit cascaded Shift Register
74396		16	v16		K555IR43		ИР43				Octal storage Registers, parallel access
74398		20	v16								Quad 2-input Multiplexers, storage and complementary Outputs
74399		16	v15		K555KP20		КП20				Quad 2-input Multiplexer, storage
745400		18	RAM								4096-bit SRAM (4k x 1), Open Collector Outputs
74F401		14	TBD								Cyclic Redundancy Check Generator/Checker
745401		18	RAM								4096-bit SRAM (4k x 1), Three-State Outputs
74F402		16	TBD								Expandable Cyclic Redundancy Check Generator/Checker
74F403		24	FIFO								64-bit FIFO memory (16x4)
745405		16	v18								1 out of 8 Binary Decoder (equivalent to i8205)
74F410		18	RAM								Register Stack-16 x 4 RAM Three-State Output Register
74412		24	v17								Multi-mode Buffered 8-bit Latches (equivalent to Intel 3212/8212)
74413		16	FIFO								256-bit FIFO memory (64x4)
745416		16	v19								4-bit Data bus sender/receiver (=Intel 8216)
74420		48	n/a								32-bit check bit / syndrome bit generator
74422		14	v22								retriggerable monostable Multivibrators, two inputs (adapter required)
74423		16	v22								Dual retriggerable monostable Multivibrator (adapter required)
74425		14	v16								Quad Bus Buffer with Three-State Outputs
74426		14	v16								Quad Bus Buffer with Three-State Outputs
74F430		28	TBD								Cyclic Redundancy Checker/Corrector
74F432		24	v18								Multi-mode Buffered 8-bit Latches, inverted Outputs
74F433		24	FIFO								256-bit FIFO memory (64x4)
74436		16	v18								Line Driver/memory Driver circuits - MOS memory interface, damping Output resistor
74437		16	v18								Line Driver/memory Driver circuits - MOS memory interface
74440		20	v17								Quad tridirectional Bus Transceiver, non-inverting Outputs
74441		20	v17								Quad tridirectional Bus Transceiver, inverting Outputs
74442		20	v17								Quad tridirectional Bus Transceiver, non-inverting Outputs
74443		20	v17								Quad tridirectional Bus Transceiver, inverting Outputs
74444		20	v17								Quad tridirectional Bus Transceiver, inverting and non-inverting Outputs
74445		16	v13								BCD-to-Decimal Decoders/Drivers
74446		16	v18								Quad Bus Transceivers, direction controls, inverting Outputs
74447		16	v16								BCD to 7-segment Decoder/Driver
74448		20	v17								Quad tridirectional Bus Transceiver, inverting and non-inverting Outputs
74449		16	v18								Quad Bus Transceivers, direction controls, non-inverting Outputs
745450		16	ROM								8192-bit PROM (1024x8) with power-down
745451		16	ROM								8192-bit PROM (1024x8) with power-down
74452		16	TBD								Dual Decimal Counter (=MCC4052, MCC4352)
74453		16	TBD								Dual Binary Counter (=MCC4053, MCC4353)
74454		24	TBD								Dual Decade Up/Down Counter
74456		16	v18								4-bit NBCD Full Adder
74461		24	v17								8-Bit Presettable Binary Counter
74465		20	v17	KR1533AP14	K555AP14		АП14				Octal Buffer, non-inverting Outputs
74466		20	v13	KR1533AP15	K555AP15		АП15				Octal Buffers, inverting Outputs
74467		20	v13								Octal Buffers, non-inverting Outputs
74468		20	v13								Octal Buffers, inverting Outputs
74470		16	ROM								2048-bit PROM (256x8)

Identifier	J	Pins	Status	UdSSR	UdSSR	DDR	Cyrillic	Philips	Siemens	Setting	Remark
74471		20	ROM								2048-bit PROM (256x8)
74472		20	ROM								4096-bit PROM (512x8)
74473		20	ROM								4096-bit PROM (512x8)
74474		24	ROM								4096-bit PROM (512x8)
74475		24	ROM								4096-bit PROM (512x8)
74476		18	ROM								4096-bit PROM (1024x4)
74477		18	ROM								4096-bit PROM (1024x4)
74478		16	ROM								8192-bit PROM (1024x8) with power-down
74479		16	ROM								8192-bit PROM (1024x8) with power-down
74484		20	TBD								BCD-to-Binary converter (mask programmed SN74S371 ROM)
74485		20	TBD								Binary-to-BCD converter (mask programmed SN74S371 ROM)
74490		16	v13								Dual decade Counter
74518		20	v13								8-bit Comparator, Open Collector
74519		20	v13								8-bit Comparator, Open Collector
74520		20	v13								8-bit Comparator, inverting Output
74521		20	v15		KR1531SP2		CP2				8-bit Comparator, inverting Output
74522		20	v13								8-bit Comparator, inverting Output, Open Collector
74524		20	v22								8-bit registered Comparator
74526		20	v18								Fuse programmable Identity Comparator, 16-bit (assumes that all fuses are unset)
74527		20	v18								Fuse programmable Identity Comparator, 8-bit + 4-bit conventional Identity Comparator (assumes that all fuses are unset)
74528		16	v18								Fuse programmable Identity Comparator, 12-bit (assumes that all fuses are unset)
74533		20	v15		K555IR40		IP40				Octal transparent Latch, inverting Outputs
74534		20	v15		KR1531IR41		IP41				Octal Register, inverting Outputs
74535		20	v28								Octal transparent Latch, inverting Outputs
74536		20	v28								Octal Register, inverting Outputs
74537		20	v18		K555ID22		ИД22				1 of 10 Decoder / BCD to Decimal Decoder
74538		20	v18								1 of 8 Decoder with 3-state Outputs
74539		20	v18								Dual 2-line to 4-line Decoder/Demultiplexer
74540		20	v15			DL540D					Octal Buffers and Line Drivers
74541		20	v15			DL541D					Octal Buffers and Line Drivers
74543		24	v17								Octal registered Transceiver, non-inverting
74544		24	v17								Octal registered Transceiver, inverting
74545		20	v18								Octal bidirectional transceiver, non-inverting
74546		24	v22								8-bit bidirectional registered transceiver, non-inverting
74547		24	v22								8-bit bidirectional latched transceiver, non-inverting
74F547		20	v22								3 to 8 Decoder/Multiplexer
74F548		20	v22								3 to 8 Decoder/Multiplexer
74550		28	TBD								Octal registered Transceiver with Status Flags, non-inverting
74551		28	TBD								Octal registered Transceiver with Status Flags, inverting
74560		20	v18								4-bit decade Counter
74561		20	v18								4-bit Binary Counter
74563		20	v15								8-bit D-Type transparent Latch, inverting Outputs
74564		20	v15								8-bit D-Type edge-triggered Register, inverting Outputs
74566		24	v22								8-bit bidirectional registered transceiver, inverting
74567		24	v22								8-bit bidirectional latched transceiver, inverting
74568		20	v17								4-bit Decade Up/Down Counter
74569		20	v17								4-bit Binary Up/Down Counter
74570		16	ROM								2048-bit PROM (512x4)
74571		20	ROM								2048-bit PROM (512x4)
74572		18	ROM								4096-bit PROM (1024x4)
74573		18	ROM								4096-bit PROM (1024x4)
74LS573		20	v15		K555IR33		IP33				Octal D Latch with Tri-State Outputs (all, except 74LS573)
74574		20	v15		K555IR37		IP37				Octal D-Type edge-triggered Flip-Flop
74575		20	v17								Octal D-Type edge-triggered Flip-Flop, synchronous Clear
74576		20	v16								Octal D-Type edge-triggered Flip-Flop, inverting Outputs
74577		24	v18								Octal D-Type edge-triggered Flip-Flop, synchronous Clear, inverting Outputs
74579		20	v18								8-bit bidirectional Binary Counter (insert at position 2)
74580		20	v16								Octal D-Type transparent Latch, inverting Outputs
74582		24	TBD								4-bit BCD arithmetic Logic Unit
74583		16	v18								4-bit BCD Adder
74588		20	v18								Octal bidirectional transceiver, non-inverting
74589		16	v13								8-bit Shift Register with input Latch with Three-State Outputs
74590		16	v16								8-bit Binary Counter, Three-State Register Outputs
74591		16	v18								8-bit Binary Counter, Open Collector Register Outputs
74592		16	v18								8-bit Binary Counter, Parallel Input Registers
74593		16	v18								8-bit Binary Counter, Parallel Tree-State I/O input Registers/Counter Outputs
74594		16	v18								8-bit Shift Registers, Serial-In, Parallel-Out, Output Latches
74595		16	v19		K555IR52		IP52				8-bit Shift Registers, Serial-In, Parallel-Out, Output Latches, Output enable
74596		16	v19								8-bit Shift Registers, Serial-In, Parallel-Out, Output Latches, Output enable
74597		16	v13								Serial-out Shift Register with input Latches
74598		20	v22								8-bit Shift Register, Selectable Parallel-In/Out input Latches
74599		16	v18								8-bit Shift Registers, Serial-In, Parallel-Out, Output Latches
74604		28	v18								Octal 2-input Multiplexer, Latch, high-speed, Three-State
74605		28	v18								Octal 2-input Multiplexer, Latch, high-speed, Open Collector
74606		28	v18								Octal 2-input Multiplexer, Latch, glitch-free, Three-State
74607		28	v18								Octal 2-input Multiplexer, Latch, glitch-free, Open Collector
74620		20	v13		K555AP26		АП26				Octal Bus Transceiver, inverting, Three-State Outputs
74621		20	v13								Octal Bus Transceiver, non-inverting, Open Collector
74622		20	v13								Octal Bus Transceiver, inverting
74623		20	v13								Octal Bus Transceiver, non-inverting, Three-State Outputs
74638		20	v15								Octal Bus Transceiver, inverting Outputs
74639		20	v15								Octal Bus Transceiver, non-inverting Outputs
74640		20	v15		K555AP9		АП9				Octal Bus Transceiver, inverting Outputs
74641		20	v15								Octal Bus Transceiver, non-inverting Outputs
74642		20	v15								Octal Bus Transceiver, inverting Outputs
74643		20	v15		K555AP16		АП16				Octal Bus Transceiver, mix of inverting and non-inverting Outputs
74644		20	v15								Octal Bus Transceiver, mix of inverting and non-inverting Outputs
74645		20	v13								Octal Bus Transceiver, non-inverting Outputs
74646		24	v19		K555AP10		АП10				Octal Bus Transceiver/Latch/Multiplexer, non-inverting Outputs, Three-State
74647		24	v19								Octal Bus Transceiver/Latch/Multiplexer, non-inverting Outputs, Open-Collector
74648		24	v19								Octal Bus Transceiver/Latch/Multiplexer, inverting Outputs, Three-State
74649		24	v19								Octal Bus Transceiver/Latch/Multiplexer, inverting Outputs, Open-Collector
74651		24	v17		K555AP17		АП17				Octal Bus Transceiver/register, inverting Outputs
74652		24	v17		K555AP24		АП24				Octal Bus Transceiver/register, non-inverting Outputs
74653		24	v17								Octal Bus Transceiver/register, inverting Outputs
74654		24	v17								Octal Bus Transceiver/register, non-inverting Outputs
74657		24	v22								Octal bidirectional transceiver with 8-bit parity generator/checker (insert at position 2)
74666		24	v17								8-bit D-Type transparent read-back Latch, non-inverting
74667		24	v17								8-bit D-Type transparent read-back Latch, inverting
74668		16	v17								Synchronous 4-bit decade Up/Down Counter
74669		16	v17								Synchronous 4-bit Binary Up/Down Counter
74670		16	RAM		K555IR26		IP26				4 by 4 Register File with Three-State Outputs
74671		20	v22								4-bit bidirectional Shift Register/Latch/Multiplexer, direct Clear
74672		20	v22								4-bit bidirectional Shift Register/Latch/Multiplexer, synchronous Clear

Identifier	J	Pins	Status	UdSSR	UdSSR	DDR	Cyrillic	Philips	Siemens	Setting	Remark
74673		24	v17								16-bit serial-in, serial/parallel-out Shift Register, Output storage Registers
74674		24	v21								16-bit serial-in, serial/parallel-out Shift Register, Output storage Registers
74675		24	TBD								16-bit serial-in, serial/parallel-out Shift Register
74676		24	TBD								16-bit serial/parallel-in, serial-out Shift Register
74677		24	v18								16-bit Address Comparator, Enable
74678		24	v19								16-bit Address Comparator, Latch
74679		20	v18								12-bit Address Comparator, Enable
74680		20	v18								12-bit Address Comparator, Latch
74681		20	v22								4-bit parallel Binary Accumulator
74682		20	v16								8-bit Magnitude Comparator, P>Q Output
74683		20	v16								8-bit Magnitude Comparator, P>Q Output, Open Collector
74684		20	v16								8-bit Magnitude Comparator, P>Q Output
74685		20	v16								8-bit Magnitude Comparator, P>Q Output, Open Collector
74686		24	v18								8-bit Magnitude Comparator, P>Q Output, Enable
74687		24	v18								8-bit Magnitude Comparator, P>Q Output, Enable
74688		20	v15								8-bit Magnitude Comparator, Enable
74689		20	v13								8-bit Magnitude Comparator, Enable, Open Collector
74690		20	v18								4-bit Decimal Counter/Latch/Multiplexer, asynchronous Clear
74691		20	v18								4-bit Binary Counter/Latch/Multiplexer, asynchronous Clear
74692		20	v18								4-bit Decimal Counter/Latch/Multiplexer, synchronous Clear
74693		20	v18								4-bit Binary Counter/Latch/Multiplexer, synchronous Clear
74696		20	v21								4-bit Decimal Up/Down Counter/register/Multiplexer, asynchronous Clear
74697		20	v21								4-bit Binary Up/Down Counter/register/Multiplexer, asynchronous Clear
74698		20	v21								4-bit Decimal Up/Down Counter/register/Multiplexer, synchronous Clear
74699		20	v21								4-bit Binary Up/Down Counter/register/Multiplexer, synchronous Clear
74720		24	v28								Multilevel Pipeline Registers
74721		24	v28								Multilevel Pipeline Registers
74740		20	v15								Octal Buffer, inverting Outputs
74741		20	v13								Octal Buffer, non-inverting Outputs
74744		20	v15								Octal Buffer with non-inverted Three-State Outputs
74748		16	v14								8 to 3-line priority encoder (glitch-less)
74756		20	v15								Octal Buffer, inverting Outputs, Open Collector and Schmidt Trigger
74757		20	v13								Octal Buffer, non-inverting Outputs, Open Collector and Schmidt Trigger
74758		20	v18								Quad Bus Transceivers, inverting Outputs, Open-Collector
74759		20	v18								Quad Bus Transceivers, non-inverting Outputs, Open-Collector
74760		20	v15								Octal Buffer/line Driver, non-inverting Outputs
74762		20	v18								Octal Buffer/line Driver, inverting and non-inverting Outputs
74763		20	v18								Octal Buffer/line Driver, inverting Outputs, complementary enable inputs
74779		16	v25								8-bit bidirectional Binary Counter (insert at position 5)
74793		20	v19								8-bit Latch, read-back
74794		20	v19								8-bit Register, read-back
74795		20	v16								Octal Buffer, non-inverting, common enable
74796		20	v16								Octal Buffer, inverting, common enable
74797		20	v16								Octal Buffer, non-inverting, enable for 4 Buffers each
74798		20	v16								Octal Buffer, inverting, enable for 4 Buffers each
74800		20	v19								Triple 4-input AND/NAND Drivers
74802		20	v19								Triple 4-input OR/NOR Drivers
74804		20	v15								Hex 2-input NAND Drivers
74805		20	v15								Hex 2-input NOR Drivers
74808		20	v17								Hex 2-input AND Drivers
74810		14	v17								Quad 2-input XNOR Gates
74821		24	v13								10-bit bus interface Flip-Flop
74822		24	v19								10-bit bus interface Flip-Flop, inverting inputs
74823		24	v13								9-bit D-Type Flip-Flops, Clear and Clock enable inputs
74824		24	v13								9-bit D-Type Flip-Flops, Clear and Clock enable inputs, inverting inputs
74825		24	v13								8-bit D-Type Flip-Flop, Clear and Clock enable inputs
74826		24	v19								8-bit D-Type Flip-Flop, Clear and Clock enable inputs, inverting inputs
74827		24	v24								10-bit Buffer, non-inverting
74828		24	v24								10-bit Buffer, inverting
74832		20	v17								Hex 2-input OR Drivers
74841		24	v19								10-bit D-Type Flip-Flop
74842		24	v19								10-bit D-Type Flip-Flop, inverting inputs
74843		24	v18								9-bit D Flip-Flops, Clear and Set inputs
74844		24	v18								9-bit D Flip-Flops, Clear and Set inputs, inverting inputs
74845		24	v19								8-bit D Flip-Flops, Clear and Set inputs
74846		24	v19								8-bit D Flip-Flops, Clear and Set inputs, inverting inputs
74848		16	v18								8 to 3-line priority encoder (glitch-less)
74850		28	v19								1 of 16 Data Selector/Multiplexer, Clocked select
74851		28	v19								1 of 16 Data Selector/Multiplexer
74852		24	TBD								8-bit universal transceiver Port Controller
74856		28	TBD								8-bit universal transceiver Port Controller
74857		24	v13								Hex 2-line to 1-line Multiplexer
74861		24	v24								10-bit Bus Transceiver, non-inverting
74862		24	v24								10-bit Bus Transceiver, inverting
74863		24	v24								9-bit Bus Transceiver, non-inverting
74864		24	v24								9-bit Bus Transceiver, inverting
74866		28	v24								8-bit Magnitude Comparator with Latches
74867		24	v22								synchronous 8-bit Up/Down Counter, asynchronous Clear
74869		24	v18								synchronous 8-bit Up/Down Counter, synchronous Clear
74870		24	RAM								Dual 16x4 Register files (16 x 4)
74871		24	RAM								Dual 16x4 Register files (16 x 4)
74873		24	v18	KR531R34			ИР34				Dual 4-bit transparent Latch with Clear
74874		24	v18	KR531R38			ИР38				Dual 4-bit edge-triggered D Flip-Flops with Clear
74876		24	v18								Dual 4-bit edge-triggered D Flip-Flops with Clear, inverting Outputs
74878		24	v18								Dual 4-bit D-Type Flip-Flop, synchronous Clear, non-inverting Outputs
74879		24	v18								Dual 4-bit D-Type Flip-Flop, synchronous Clear, inverting Outputs
74880		24	v18								Dual 4-bit transparent Latch with Clear, inverting Outputs
74881		24	v24								4-bit arithmetic Logic Unit
74885		24	v18								8-bit Magnitude Comparator
74ALS900		14	v17								Quad 2-input NAND Gate
74C901		14	v13								Hex inverting CMOS to TTL Buffer
74ALS902		14	v17								Quad 2-input NOR Gate
74C902		14	v13								Hex non-inverting CMOS to TTL Buffer
74ALS903		14	v17								Quad 2-input NAND Gate with Open Collector Outputs
74C903		14	v18								Hex inverting TTL to CMOS Buffer
74C904		14	v18								Hex non-inverting TTL to CMOS Buffer
74C906		14	v13								Hex inverting NMOS Buffer
74C910		18	RAM								RAM 64 x 4 bit
74C914		14	v18								Hex Schmitt Trigger Inverter
74C915		18	v18								7-segment to BCD
74C920		22	RAM								RAM 256 x 4 bit
74C921		18	RAM								RAM 256 x 4 bit
74C929		16	RAM								RAM 1024 x 1 bit
74C930		16	RAM								RAM 1024 x 1 bit

Identifier	J	Pins	Status	UdSSR	UdSSR	DDR	Cyrillic	Philips	Siemens	Setting	Remark
745940		20	v18								Octal Buffer, inverting Outputs
745941		20	v18								Octal Buffer, non-inverting Outputs
74C989		16	RAM								RAM 16 x 4 bit
74990		20	v18								8-bit D-Type transparent read-back Latch, non-inverting
74991		20	v19								8-bit D-Type transparent read-back Latch, inverting
74992		24	v19								9-bit D-Type transparent read-back Latch, non-inverting
74993		24	v19								9-bit D-Type transparent read-back Latch, inverting
74994		24	v18								10-bit D-Type transparent read-back Latch, non-inverting
74995		24	v23								10-bit D-Type transparent read-back Latch, inverting
74996		24	v22								8-bit D-Type edge-triggered read-back Latch
741000		14	v18	KR1553LA21			ЛА21			7400	Quad 2-input NAND Gate
741002		14	v18	KR1553LE1			ЛЕ1			7402	Quad 2-input NOR Gate
741003		14	v18	KR1553LA23			ЛА23			7403	Quad 2-input NAND Gate
741004		14	v18	KR1553LH8			ЛH8			7404	Hex inverting Buffer
741005		14	v18	KR1553LH10			ЛH10			7405	Hex inverting Buffer
741008		14	v18	KR1553LH8			ЛH8			7408	Quad 2-input AND Gate
741010		14	v18	KR1553LA24			ЛА24			7410	Triple 3-input NAND Gate
741011		14	v18	KR1553LI10			ЛИ10			7411	Triple 3-input AND Gate
741020		14	v18	KR1553LA22			ЛА22			7420	Dual 4-input NAND Gate
741032		14	v18	KR1553LL4			ЛЛ4			7432	Quad 2-input OR Gate
741034		14	v18	KR1553LP16			ЛП16			7434	Hex non-inverting Buffer
741035		14	v18	KR1553LP17			ЛП17			7435	Hex non-inverting Buffer
741240		20	v18							74240	Octal Buffer / line Driver, inverting (lower-power version of 74x240)
741241		20	v18							74241	Octal Buffer / line Driver, non-inverting (lower-power version of 74x241)
741242		14	v18							74242	Quad Bus Transceiver, inverting (lower-power version of 74x242)
741243		14	v18							74243	Quad Bus Transceiver, non-inverting (lower-power version of 74x243)
741244		20	v18							74244	Octal Buffer / Driver, non-inverting (lower-power version of 74x244)
741245		20	v18							74245	Octal Bus Transceiver (lower-power version of 74x245)
741620		20	v18							74620	Octal Bus Transceiver, inverting
741621		20	v18							74621	Octal Bus Transceiver, non-inverting
741622		20	v18							74622	Octal Bus Transceiver, inverting
741623		20	v18							74623	Octal Bus Transceiver, non-inverting
741638		20	v18							74638	Octal Bus Transceiver, inverting (lower-power version of 74x638)
741639		20	v18							74639	Octal Bus Transceiver, non-inverting (lower-power version of 74x639)
741640		20	v18							74640	Octal Bus Transceiver, inverting (lower-power version of 74x640)
741641		20	v18							74641	Octal Bus Transceiver, non-inverting (lower-power version of 74x641)
741642		20	v18							74642	Octal Bus Transceiver, inverting (lower-power version of 74x642)
741643		20	v18							74643	Octal Bus Transceiver, inverting and non-inverting (lower-power version of 74x643)
741644		20	v18							74644	Octal Bus Transceiver, inverting and non-inverting (lower-power version of 74x644)
741645		20	v18							74645	Octal Bus Transceiver, non-inverting (lower-power version of 74x645)
742540		20	v28								Octal Buffers and Line Drivers
742541		20	v28								Octal Buffers and Line Drivers
742708		14	ROM								8192-bit PROM (1024x8)
743037		16	v18								Quad 2-input NAND (insert at position 4)
743708		14	ROM								8192-bit PROM (1024x8)
747001		14	v16								Quad 2-input AND Gate
747002		14	v16								Quad 2-input NOR Gate
747014		14	v16								Hex non-inverting Buffer
747032		14	v16								Quad 2-input OR Gates
747080		14	TBD								16-bit parity generator / checker
747266		14	v17								Quad 2-input XNOR Gate
747403		16	FIFO								256-bit FIFO memory (64x4)
747404		16	FIFO								320-bit FIFO memory (64x5)
748541		20	v18								8-bit Buffer, selectable inverting/non-inverting
749034		20	v17								Nine-wide Buffer, inverting
749035		20	v17								Nine-wide Buffer
749114		20	v17								Nine-wide Buffer, inverting
749115		20	v17								Nine-wide Buffer
749134		20	v17								Nine-wide Buffer, inverting
749135		20	v17								Nine-wide Buffer
749240		24	v17								9-bit Buffer / line Driver, inverting
749244		24	v17								9-bit Buffer / line Driver, non-inverting
749245		24	v17								9-bit bidirectional transceiver, non-inverting
75121		16	v18								Dual line Driver
75122		16	v18								Triple line Driver (N8T14)
75123		16	v18								Dual line Driver
75124		16	v18								Triple line Driver
75125		16	v18								7x line receiver, inverting Outputs (insert at position 9)
75127		16	v18								7x line receiver, inverting Outputs
75138		16	v18								Quad Bus Transceiver
75140		8	v22								Dual line receiver (insert at position 6)
75154		16	v20								Quad line receiver (insert at position 7)
75160		20	v16								Octal Bus Transceiver
75172		16	v18								Quad line Driver (SN65173)
75173		16	v18								Quad line Receiver
75189		14	v15								Quad Line Receiver (MC1489)
75361-8		8	v27								Dual NAND high power (in DIP-8, insert at position 6)
75361-14		14	v27			D461D					Dual NAND high power (in DIP-14)
75450		14	v17								Dual AND high power
75451		8	v14	K155LA5			ЛА5				Dual AND high power (insert at position 6)
75452		8	v14	K155LA18			ЛА18				Dual NAND high power (insert at position 6)
75453		8	v14	K155LL2			ЛЛ18				Dual OR high power (insert at position 6)
75454		8	v14								Dual NOR high power (insert at position 6)
75460		14	v17	K1102AP10			АП10				Dual AND high power
75461		8	v17	K1102AP11			АП11				Dual AND high power (insert at position 6)
75462		8	v17	K1102AP12			АП12				Dual NAND high power (insert at position 6)
75463		8	v17	K1102AP13			АП13				Dual OR high power (insert at position 6)
75464		8	v17	K1102AP14			АП14				Dual NOR high power (insert at position 6)
75466		16	v18								7x Darlington Arrays
75467		16	v18								7x Darlington Arrays
75468		16	v17								7x Darlington Arrays
75469		16	v18								7x Darlington Arrays
75470		14	v18								Dual AND high power
75471		8	v18								Dual AND high power (insert at position 6)
75472		8	v18								Dual NAND high power (insert at position 6)
75473		8	v18								Dual OR high power (insert at position 6)
75474		8	v18								Dual NOR high power (insert at position 6)
75491		14	v21								Quad digital Driver MOS to LED (insert at position 4)
75492		14	v21								Hex digital Driver MOS to LED (insert at position 4)
75494		16	v23	KR1010KT1			КТ1				Hex digit Driver
75497		16	v18								MOS to LED 7-Channel Driver
75498		20	v18								MOS to LED 9-Channel Driver
4000		14	v14		K176LP4		ЛП4				Dual 3-input NOR Gate + 1 NOT Gate
4001		14	v14		K176LE5		ЛЕ5				Quad 2-input NOR Gate

Identifier	J	Pins	Status	UdSSR	UdSSR	DDR	Cyrillic	Philips	Siemens	Setting	Remark
4002	14	v14			K176LE6		ЛЕ6				Dual 4-input NOR Gate
4006	14	v20			K176IR10		ИР10				18-stage Shift Register (four independent with common Clock: two 4-stage, two 5-stage with Q4 tap)
4007	14	v17			K176LP1		ЛП1				Dual complementary transistor pair + 1 NOT Gate (pin 5 and 8 untested)
4008	16	v14			K176IM1		ИМ1				4-bit Binary Full Adder
4009	16	v15			K176PU2		ПУ2				Hex Inverter Gate, Dual power supply, can drive 1 TTL/DTL load (replaced by 4049)
4010	16	v15			K176PU3		ПУ4				Hex Buffer Gate, Dual power supply, can drive 1 TTL/DTL load (replaced by 4050)
4011	14	v14			K176LA7		ЛА7				Quad 2-input NAND Gate
4012	14	v14			K176LA8		ЛА8				Dual 4-input NAND Gate
4013	14	v15			K176TM2		ТМ2				Dual D-Type Flip-Flop
4014	16	v15									8-stage parallel in Shift Register (synchronous parallel load, serial in, Q6/Q7/Q8 out) (see 4021)
4015	16	v14			K176IR2		ИР2				Dual 4-stage Shift Register (two independent: serial in, Q1/Q2/Q3/Q4 out, reset, Clock)
4016	14	v14			K176KT1		КТ1				Quad bilateral switch
4017	16	v14			K176IE8		ИЕ8				Decade Counter with 10 decoded Outputs (5-stage Johnson Counter)
4018	16	v16			K561IE19		ИЕ19				Presetable divide-by-N Counter
4019	16	v14			K561LS2		ЛС2				Quad AND/OR select Gate
4020	16	v14			K561IE16		ИЕ16				14-stage Binary ripple Counter
4021	16	v15									8-stage parallel in Shift Register (synchronous parallel load, serial in, Q6/Q7/Q8 out) (see 4014)
4022	16	v14			K561IE9		ИЕ9				Octal Counter with 8 decoded Outputs (4-stage Johnson Counter)
4023	14	v14			K176LA9		ЛА9				Triple 3-input NAND Gate
4024	14	v14									7-stage Binary ripple Counter
4025	14	v15			K176LE10		ЛЕ10				Triple 3-input NOR Gate
4026	16	v15			K176IE4		ИЕ4				Decade Counter with decoded 7-segment display Outputs and display enable
4027	16	v14			K176TV1		ТВ1				Dual J-K Master-Slave Flip-Flop
4028	16	v14			K176ID1		ИД1				BCD to Decimal (1-of-10) Decoder active HIGH Output
4029	16	v14			K561IE14		ИЕ14				Presetable Up/Down Counter, Binary or BCD-decade
4030	14	v15			K176LP2		ЛП2				Quad XOR Gate (replaced by 4070)
4031	16	v23 (!)			K176IR4		ИР4				64-stage Shift Register (no loop test possible, not Fully tested, Output signal test only)
4032	16	v16									Triple serial Adder
4033	16	v15			K176IE5		ИЕ5				Decade Counter with decoded 7-segment display Outputs and ripple blanking
4034	24	v17			K561IR6		ИР6				8-stage bidirectional parallel/serial input/Output Register
4035	16	v16			K561IR9		ИР9				4-stage parallel-in/parallel-out Shift Register
4036	24	RAM									RAM 4 x 8 bit
4038	16	v16									Triple serial Adder
4039	24	RAM									RAM 4 x 8 bit
4040	16	v14			KR1561IE20		ИЕ20				12-stage Binary ripple Counter
4041	14	v14									Quad Buffer/Inverter (two Outputs for each input) (4 times standard "B" drive)
4042	16	v14			K561TM3		ТМ3				Quad D-Type Latch
4043	16	v14			K561TR2		ТР2				Quad NOR R-S Latch with tri-state Outputs
4044	16	v15									Quad NAND R-S Latch with tri-state Outputs
4045	16	n/a									21-stage Counter
4046	16	n/a			KR1561GG1		ГГ1				Phase-locked loop with VCO
4047	14	n/a									Monostable/astable Multivibrator
4048	16	v15									Multifunctional expandable 8-input Gate with tri-state Output
4049	16	v15			K561LH2		ЛH2				Hex Inverter Gate, can drive 2 TTL/RTL loads or 4 four 74LS loads (insert at position 9)
4050	16	v14			K561PU4		ПУ4				Hex Buffer Gate, can drive 2 TTL/RTL loads or 4 four 74LS loads (insert at position 9)
4051	16	v15			K561KP2		КП2				8-Channel analog Multiplexer/Demultiplexer
4052	16	v15			K561KP1		КП1				Dual 4-Channel analog Multiplexer/Demultiplexer
4053	16	v14			KR1561KP5		КП5				Triple 2-Channel analog Multiplexer/Demultiplexer
4054	16	v15									BCD to 7-segment Decoder/LCD Driver
4055	16	v15									BCD to 7-segment Decoder/LCD Driver with "display-frequency" Output
4056	16	v15									BCD to 7-segment Decoder/LCD Driver with strobed-latch function
4059	24	v18			K561IE15		ИЕ15				Programmable divide-by-N Counter
4060	16	v16									14-stage Binary ripple Counter and Oscillator, Schmitt Trigger inputs
4061	16	RAM			K176RU2		РУ2				RAM 256 x 1 bit
4063	16	v16									4-bit digital Comparator
4066	14	v14 (*)			K561KT3		КТ3				Quad analog switch (low "ON" resistance)
4067	24	v16									16-Channel analog Multiplexer/Demultiplexer (1-of-16 switch)
4068	14	v15									8-input NAND/AND Gate (2 Outputs)
4069	14	v14			564PU7		ПУ7				Hex Inverter
4070	14	v14			KR1561LP14		ЛП14				Quad 2-input XOR Gate
4071	14	v14									Quad 2-input OR Gate
4072	14	v14									Dual 4-input OR Gate
4073	14	v14									Triple 3-input AND Gate
4075	14	v14									Triple 3-input OR Gate
4076	16	v14			KR1561IR14		ИР14				Quad D-Type Register with tri-state Outputs
4077	14	v14									Quad 2-input XNOR Gate
4078	14	v14									8-input NOR/OR Gate (2 Outputs)
4081	14	v14			K561LU2		ЛУ2				Quad 2-input AND Gate
4082	14	v14									Dual 4-input AND Gate
4085	14	v15									Dual 2-wide, 2-input AND/OR invert (AOI)
4086	14	v15									Expandable 4-wide, 2-input AND/OR invert (AOI)
4089	16	n/a									Binary rate Multiplier
4093	14	v14			K561TL1		ТЛ1				Quad 2-input NAND Gate, Schmitt Trigger inputs
4094	16	v14			KR1561PR1		ПР1				8-stage Shift-and-store bus
4095	16	v16									Gated J-K Flip-Flop (non-inverting)
4096	16	v16									Gated J-K Flip-Flop (inverting and non-inverting)
4097	24	v24									Differential 8-Channel analog Multiplexer/Demultiplexer
4098	16	v22			KR1561AG1		АГ1				Dual one-shot monostable
4099	16	v14									8-bit addressable Latch
40014	14	v18									Hex Schmitt Trigger Inverter
40032	14	v28									Quad 2-input OR Gate
40097	16	v18									Hex Buffer with non-inverted Three-State Outputs
40098	16	v18									Hex Buffer with inverted Three-State Outputs
40100	16	n/a									32-stage left/right Shift Register
40101	14	v13			1526IP6		ИП6				9-bit parity generator/checker
40102	16	v17									Presetable 2-decade BCD down Counter
40103	16	v17									Presetable 8-bit Binary down Counter
40104	16	v16									4-bit bidirectional universal Shift Register with Output enable
40105	16	FIFO									4-bit x 16 word FIFO Register
40106	14	v14									Hex Inverter Gate, Schmitt Trigger inputs
40107	8	v16			KR1561LA10		ЛА10				Dual 2-input NAND Gate with 136mA Open-drain Driver (32 times standard "B" sink) (insert at position 6)
40109	16	v16			1526PU6		ПУ6				Quad Level Shifter
40110	16	v16									Up/down decade Counter, Latch, 7-segment Decoder, LED Driver
40116	22	v17			564PU9		ПУ9				8-bit bidirectional CMOS-to-TTL level converter (checks logic only, not levels)
40117	14	n/a									Programmable Dual 4-bit terminator
40147	16	v23									10-line to 4-line (BCD) priority encoder
40160	16	v13									Decade Counter/asynchronous Clear
40161	16	v14			K561IE21		ИЕ21				Binary Counter/asynchronous Clear
40162	16	v14									Decade Counter/synchronous Clear
40163	16	v16									Binary Counter/synchronous Clear
40174	16	v14									Hex D-Type Flip-Flop
40175	16	v15									Quad D-Type Flip-Flop
40192	16	v16									Presetable 4-bit Up/Down BCD Counter
40193	16	v16									Presetable 4-bit Up/Down Binary Counter

Identifier	J	Pins	Status	UdSSR	UdSSR	DDR	Cyrillic	Philips	Siemens	Setting	Remark
40194	16	v16									4-bit bidirectional universal Shift Register with reset
40240	20	v16									Buffer/Line Driver; inverting (tri-state)
40244	20	v16									Buffer/line Driver; non-inverting (tri-state)
40245	20	v16									Octal Bus Transceiver; (tri-state) Outputs
40257	16	v16									Quad 2-line to 1-line Data Selector/Multiplexer (tri-state)
40373	20	v16									Octal D-Type transparent Latch (tri-state)
40374	20	v16									Octal D-Type Flip-Flop; positive-edge Trigger (tri-state)
40511	16	v18									BCD to 7-segment Decoder/Driver
4316	16	v17									Quad Analog Switch/Multiplexer/Demultiplexer (only digitally tested)
4428	14	v21									Binary to Octal Decoder
4501	16	v16									Triple Gate
4502	16	v15			KP561LN1		ЛН1				Hex inverting Buffer (tri-state)
4503	16	v13			K561LH3		ЛН3				Hex non-inverting Buffer with tri-state Outputs
4504	16	v13									Hex voltage level Shifter for TTL-to-CMOS or CMOS-to-CMOS operation (insert at position 9)
4505	14	RAM									RAM 64 x 1 bit
4506	16	v16									Dual 2-2 AND-OR-INVERT
4507	14	v16									Quad 2-input Exclusive-OR Gate
4508	24	v15									Dual 4-bit Latch with tri-state Outputs
4510	16	v15									Presettable 4-bit BCD Up/Down Counter
4511	16	v14			K1564ID23		ИД23				BCD to 7-segment Latch/decoder/Driver
4512	16	v14			KR1561KP3		КП3				8-input Multiplexer (data Selector) with tri-state Output
4513	18	v16									BCD to 7-segment Latch/decoder/Driver
4514	24	v13									1-of-16 Decoder/Demultiplexer active HIGH Output
4515	24	v13									1-of-16 Decoder/Demultiplexer active LOW Output
4516	16	v16			KR1561IE11		ИЕ11				Presettable 4-bit Binary Up/Down Counter
4517	16	n/a									Dual 64-stage Shift Register
4518	16	v13									Dual BCD up Counter
4519	16	v14			K561KP4		КП4				Quad 2-input Multiplexer (data Selector)
4520	16	v14			K561IE10		ИЕ10				Dual 4-bit Binary up Counter
4521	16	n/a									24-stage frequency Divider
4522	16	v16									Programmable BCD divide-by-N Counter
4526	16	v17									Programmable 4-bit Binary down Counter
4527	16	n/a									BCD rate Multiplier
4528	16	v22									Dual retriggerable monostable Multivibrator with reset
4529	16	v13									Dual 4-Channel analog Data Selector/Multiplexer
4530	16	v16									Dual 5-input majority logical Gate
4531	16	v15									13-input parity checker/generator
4532	16	v15									8-bit priority encoder
4534	24	n/a									Cascaded BCD Counters
4536	16	n/a									Programmable Timer
4538	16	v22									Dual retriggerable precision monostable Multivibrator
4539	16	v16									Dual 4-input Multiplexer
4541	14	n/a									Programmable Timer
4543	16	v15									BCD to 7-segment Latch/decoder/Driver with phase input
4549	16	n/a									Successive approximation Registers
4551	16	v25									Quad 2-Channel analog Multiplexer/Demultiplexer
4553	16	n/a									3-digit BCD Counter
4555	16	v14			K561ID6		ИД6				Dual 1-of-4 Decoder/Demultiplexer active HIGH Output
4556	16	v14			K561ID7		ИД7				Dual 1-of-4 Decoder/Demultiplexer active LOW Output
4557	16	TBD									1-to-64 stage variable length Shift Register
4558	16	v16									BCD to 7-segment Decoder (enable, RBI and provides active-high Output)
4559	16	n/a									Successive approximation Registers
4560	16	v16									NBCD Adder
4561	14	v16									9's complements
4566	16	n/a									Industrial time-base generator
4568	16	n/a									Phase Comparator and Programmable Counters
4569	16	TBD									Programmable divide-by-N, Dual 4-Bit Binary/BCD down Counter
4572	16	v15									Hex Gate: Quad NOT, single NAND, single NOR
4574	16	v18 (*)									Quad Comparator (insert at position 5)
4583	16	n/a									Dual adjustable Schmitt Trigger inputs, each with Buffer and Inverter Outputs, and XOR Output
4584	14	v14									Hex inverter Gate, Schmitt Trigger inputs
4585	16	v16			K561IP2		ИП2				4-bit digital Comparator
4598	18	v17									8-bit addressable Latch
4720	16	RAM									RAM 256 x 1 bit
4723	16	v18									4-bit addressable Latch
4724	16	v16									8-bit addressable Latch
4929	16	v15						FLH251			Dual NAND, Quad Inverter
4930	14	v13						FLH321			Quad 2-input NAND (insert at position 5)
4931	14	v13						FLH331			Dual 5-input NAND
4934	14	v18						FLH461			Hex inverter with Open Collector Outputs (insert at position 4)
4935	14	v18						FLH471			Hex inverter (insert at position 4)
49700	16	v15						FLL131			Dual NAND Gate, Dual AND Gate with 15V Open Collector Outputs
49701	16	v15						FLL141			Quad Drivers with Open Collector Outputs
49702	16	v15						FLI491			4-bit D Register with Clear
49703	16	v13						FLH641			Hex delay Gates
49704	16	v13						FLJ501			Dual Binary Counter (insert at position 4)
49705	16	v15						FLJ511			Dual Decimal Counter (insert at position 4)
49710	8	v24									Frequency Divider 50:1 (insert at position 7)
49711	8	v24									Frequency Divider 60:1 (insert at position 7)
49713	14	v13						FLH731			Dual 3-input NAND Schmitt Trigger
49714	8	v13									2:4 Decoder (insert at position 6)
49805	20	v24									1:5 Buffer/Clock Driver
3205	16	v14							8205		1 out of 8 Binary Decoder (equivalent to SN74S405, MH3205)
3212	24	v17							8212		use 8212, Multi-mode Buffered 8-bit Latches (equivalent to Intel 3212/8212, 74S412)
3216	16	v18							8216		use 8216, Quad parallel bidirectional bus Driver (equivalent to Intel 3216/8216/M5L8216)
3226	16	v18							8226		use 8226, Quad parallel bidirectional bus Driver, inverting Outputs (equivalent to Intel 3226/8226/M5L8226/H)
3404	16	v24									High Speed 6-Bit Latch
6529	20	v24									MOS6529, Single Port Interface (SPI)
7640	14	v18							8640		Quad NOR Unified Driver (=DS8640)
7641	16	v19							8641		Quad NOR Unified Driver (=DS8641)
7707	14	v15									MOS7707, Hex Inverter with Open Collector (=74LS06)
7708	16	v15									MOS7708, Quad 2-line to 1-line Data Selector/Multiplexer with non-inverted TS-Outputs (=74LS257)
7709	16	v13									MOS7709, Quad 2-line to 1-line Data Selector/Multiplexer with inverted TS-Outputs (=74LS258)
7711	16	v15									MOS7711, Dual 2 to 4-line Decoder/Demultiplexer (=74LS139)
7712	14	v15									MOS7712, Quad 2-input AND (=74LS08)
7713	14	v15									MOS7713, Hex Inverter (=74LS04)
7714	14	v15									MOS7714, Quad 2-input NOR (=74LS02)
7715	20	v15									MOS7715, Octal Register with Three-State Outputs (=74LS373)
7810	14	v18							8810		Quad 2-input NAND Gate with Open Collector Outputs (=DS8810)
7811	14	v18							8811		Quad 2-input NAND Gate with Open Collector Outputs (=DS8811)
7812	14	v18							8812		Hex Inverter (=DS8812)
7819	14	v18							8819		Quad 2-input AND Gate with Open Collector Outputs (=DS8819)
7833	16	v24							8833		Quad Three-State Bus Transceivers (=DM7833)
7835	16	v24							8835		Quad Three-State Bus Transceivers, inverting Outputs (=DM7835)

Identifier	J	Pins	Status	UdSSR	UdSSR	DDR	Cyrillic	Phillips	Siemens	Setting	Remark
7837		16	v20							8837	use DM8837, Hex Line Driver
7838		16	v20							8838	use DM8838, Quad NOR Unified Driver
8708		20	v15								MOS8708, Quad 2-line to 1-line Data Selector/Multiplexer with non-inverted TS-Outputs = 74LS257
8713		20	v15								MOS8713, Hex Inverter = 74LS04
7093		14	v22							8093	Quad Bus Buffer with Three-State Outputs
7094		14	v22							8094	Quad Bus Buffer with Three-State Outputs
7131		16	v20							8131	use DM8131, 6-Bit Unified Bus Comparator
7160		16	v26							8160	use DM8160, 6-Bit Unified Bus Comparator
7220		14	v24							8220	9-bit parity generator/checker (=DM8220)
74L90		14	v23							7490	4-Bit Decade Counter
74L93		14	v23							74C93	4-Bit Binary Counter
8090		16	v23								Dual NAND, Quad Inverter
8091		14	v23								Quad 2-input NAND (insert at position 5)
8092		14	v23								Dual 5-input NAND Gate
8093		14	v22								Quad Bus Buffer with Three-State Outputs
8094		14	v22								Quad Bus Buffer with Three-State Outputs
8095		16	v23								Hex Buffer with non-inverted Three-State Outputs
80C95		16	v13							8095	Hex Buffer with non-inverted Three-State Outputs
8096		16	v23								Hex Buffer with inverted Three-State Outputs
80C96		16	v13							8096	Hex Buffer with inverted Three-State Outputs
8097		16	v23								Hex Buffer with non-inverted Three-State Outputs
80C97		16	v13							8097	Hex Buffer with non-inverted Three-State Outputs
8098		16	v23								Hex Buffer with inverted Three-State Outputs
80C98		16	v13							8098	Hex Buffer with inverted Three-State Outputs
8121		16	v20								8-line to 1-Line Data Selector/Multiplexer
8123		16	v20								Quad 2-Line to 1-Line Data Selector/Multiplexer
8131		16	v20								6-Bit Unified Bus Comparator (=DM7131)
8160		16	v26								6-Bit Unified Bus Comparator (=DM7160)
8200		16	v28								4-Bit Magnitude Comparator
8205		16	v18								1 out of 8 Binary Decoder (equivalent to SN745405, MH3205)
8212		24	v17								Multi-mode Buffered 8-bit Latches (equivalent to Intel 3212/8212, 745412)
8216		16	v18	K589AP16			АП16				Quad parallel bidirectional bus Driver (equivalent to Intel 3216/8216/M5L8216)
8219		24	v17								16-line to 1-line Data Selector/Multiplexer
82C19		24	v17							8219	16-line to 1-line Data Selector/Multiplexer
8220		14	v24								9-bit parity generator/checker
8226		16	v18	K589AP26			АП26				Quad parallel bidirectional bus Driver, inverting Outputs (equivalent to Intel 3226/8226/M5L8226/MH3226)
8230		16	v25								8-input digital Multiplexer
8231		16	v25								8-input digital Multiplexer with Open-Collector Output
8232		16	TBD								8-input digital Multiplexer
8233		16	v23								Quad 2-input Multiplexer
8234		16	v23								Quad 2-input Multiplexer, Open Collector Outputs
8235		16	v21								Quad 2-input Multiplexer, Open Collector Outputs (=DEC 8275)
8241		14	v19								Quad 2-input XOR (Signetics)
8242		14	v19								4-bit Comparator with Open Collector Outputs
8250		14	v20								1-of-8 Decoder active LOW Output
8251		16	v20								BCD to Decimal (1-of-10) Decoder active LOW Output
8252		16	v20								BCD to Decimal (1-of-10) Decoder active LOW Output (=DM9301)
82562		14	v24								9-bit parity generator/checker
8263		24	v20								3-input 4-Bit Digital Multiplexer (Signetics)
8264		24	v20								3-input 4-Bit Digital Multiplexer with Enable and Open Collector Outputs (Signetics)
8266		16	v20								2-input 4-Bit Digital Multiplexer (Signetics)
8267		16	v20								2-input 4-Bit Digital Multiplexer and Open Collector Outputs (Signetics)
8270		14	v23								4-bit parallel-access Shift Register
8271		16	v23								4-bit parallel-access Shift Register, asynchronous Clear input, complementary Qd Output
8280		14	v24								Presetable decade (bi-quinary) Counter/Latch
8281		14	v24								Presetable Binary Counter/Latch
8282		20	v19								Octal Latch (=DS8282)
8283		20	v19								Octal Latch, inverted Outputs (=DS8283)
8284		14	TBD								Binary Hexadecimal synchronous Up/Down Counter
8285		14	TBD								BCD Decade synchronous Up/Down Counter
8286		20	v14								Octal Bus Transceiver, non-inverting Outputs (=DS8286)
8287		20	v14								Octal Bus Transceiver, inverting Outputs (=DS8287)
8290		14	v20								Presetable decade (bi-quinary) Counter/Latch
8291		14	v20								Presetable Binary Counter/Latch
8292		14	v24								Presetable decade (bi-quinary) Counter/Latch, low power
8293		14	v24								Presetable Binary Counter/Latch, low power
8415A		14	v20								Dual 5-input NAND Gate, Open Collector Outputs
8455A		14	v20								Dual 4-input NAND Gate
8470A		14	v20								Triple 3-input NAND Gate
8471A		14	v20								Triple 3-input NAND Gate, Open Collector Outputs
8480A		14	v20								Quad 2-input NAND Gate
8481A		14	v20								Quad 2-input NAND Gate, Open Collector Outputs
8490A		14	v20								Hex Inverter
8530		14	v19 (I)								4-Bit Decade Counter (insert at position 4)
8532		14	v19 (I)								Divide-by-12 Counter (insert at position 4)
8533		14	v19 (I)								4-Bit Binary Counter (insert at position 4)
8555		16	v28								4-Bit Programmable Decade Counter
8556		16	v28								4-Bit Programmable Binary Counter
8560		16	v28								Synchronous Up/Down Decade Counter with Clear
8563		16	v28								Synchronous Up/Down Binary Counter with Clear
8570		14	v19								8-Bit Parallel-Out Serial Shift Register with asynchronous Clear
8590		16	v19								8-Bit Serial Shift Register
8640		14	v18								Quad NOR Unified Driver (=DS7640)
8641		16	v19								Quad NOR Unified Driver (=DS7641)
86L75		16	v19							74160	Synchronous 4-Bit Decade Counter with asynchronous Clear
86L76		16	v19							74161	Synchronous 4-Bit Binary Counter with asynchronous Clear
86L93		14	v14 (I)							7493	4-Bit Binary Counter
8808A		14	v20								8-input NAND Gate
8810		14	v18								Quad 2-input NAND Gate with Open Collector Outputs (=DS7810)
8811		14	v18								Quad 2-input NAND Gate with Open Collector Outputs (=DS7811)
8812		14	v18								Hex Inverter (=DS7812)
8815A		14	v20								Dual 4-input NOR Gate
8816A		14	v20								Dual 4-input NAND Gate
8819		14	v18								Quad 2-input AND Gate with Open Collector Outputs (=DS7819)
8829A		14	v20								AND Gated J-K Master-Slave Flip-Flop, asynchronous Preset and Clear
8830		14	v15								Dual Differential Line Driver
8833		16	v24								Quad Three-State Bus Transceivers (=DM7833)
8835		16	v24								Quad Three-State Bus Transceivers, inverting Outputs (=DM7835)
8835		14	v28								Quad 2-input NOR Driver/Receiver
8837		16	v20								Hex Line Driver (=DM7837)
8838		16	v20								Quad NOR Unified Driver (=DM7838)
8840A		14	v20								Dual 2-Wide 2-input AND-OR-INVERT Gate
8848A		14	v20								2-2-2-3-input AND-OR-INVERT Gate
8855A		14	v20								Dual 4-input NAND Gate

Identifier	J	Pins	Status	UdSSR	UdSSR	DDR	Cyrillic	Phillips	Siemens	Setting	Remark
8870A		14	v20								Triple 3-input NAND Gate
8875A		14	v20								Triple 3-input NOR Gate
8880A		14	v20								Quad 2-input NAND
8881A		14	v20								Quad 2-input NAND, Open Collector Outputs
8885A		14	v20								Quad 2-input NOR Gate
8890A		14	v20								Hex Inverter
8891A		14	v20								Hex Inverter, Open Collector Outputs
9000		14	v27								J-K Master-Slave Flip-Flop
9001		14	v27								J-K Master-Slave Flip-Flop, J2 and K2 inverted
9002		14	v18								Quad 2-input NAND Gate
9003		14	v18								Triple 3-input NAND Gate
9004		14	v18								Dual 4-input NAND Gate
9007		14	v28								8-input NAND Gate
9009		14	v20								Dual Schmitt Trigger 4-input NAND Gate
9012		14	v18								Quad 2-input NAND Gate with Open Collector Outputs
9016		14	v18								Hex Inverter
9017		14	v28								Hex Inverter with Open Collector Outputs
9024		16	v18								Dual J-Not-K Positive-Edge-triggered Flip-Flop with Clear and Preset
9300		16	v20								4-Bit Parallel-Access Shift Register (=DM8300)
9301		16	v20								BCD to Decimal (1-of-10) Decoder active LOW Output (=DM8301)
9308		24	v26								Dual 4-bit Latch, Clear
9309		16	v26								Dual 4-Bit Data Selectors/Multiplexers
9310		16	v23								Synchronous 4-Bit Decade Counter with asynchronous Clear
9312		16	v28								8-input Multiplexer
9314		16	v18								Quad Latch
9316		16	v23								Synchronous 4-Bit Binary Counter with asynchronous Clear
9317		16	v28								BCD to 7-segment Decoder/Driver
9318		16	v28								8-Line to 3-Line Priority Encoder
9321		16	v28								Dual 2 to 4-line Decoder/Demultiplexer
9322		16	v20								Quad 2-Line to 1-Line Data Selector/Multiplexer (=DM8322)
9324		16	v28								5-Bit Comparator
9334		16	v24								8-Bit addressable Latch
93547		16	v24								High Speed 6-Bit Identity Comparator
93562		14	v26								9-bit parity generator/checker
9368		16	v18								BCD to 7-segment Decoder/Driver (=F9368)
9370		16	v18								BCD to 7-segment Decoder/Driver with Open Collector Outputs (F9370)
9602		16	v24					4098			Dual retriggerable precision monostable Multivibrator (=4098,4528,4538)
8H16		14	v20								Dual 4-input NAND Gate
8H70		14	v20								Triple 3-input NOR Gate
8H80		14	v20								Quad 2-input NOR Gate
8H90		14	v20								Hex Inverter
8T09		14	v24								Quad Bus Driver with Three-State Outputs, inverting
8T10		16	v17								Quad D Flip-Flop with Three-State Outputs
8T13		16	v17								Dual line Driver
8T14		16	v17								Triple line Driver
8T22		14	v22								retriggerable monostable Multivibrator (adapter required)
8T23		16	v17								Dual line Driver
8T24		16	v17								Triple line Driver
8T26		16	v17								Quad Bus Driver/Receiver Inverting Outputs
8T28		16	v17								Quad Bus Driver/Receiver
8T37		16	v20								Hex Line Driver (=8837/7837)
8T38		16	v20								Quad NOR Unified Driver (=8641)
8T80		14	v24								Quad 2-input NAND, Open Collector Outputs
8T90		14	v24								Hex Inverter, Open Collector Outputs
8T93		14	v22								Hex Inverter
8T94		14	v22								Hex Inverter
8T95		16	v17								Hex Buffer with non-inverted Three-State Outputs
8T96		16	v17								Hex Buffer with inverted Three-State Outputs
8T97		16	v17								Hex Buffer with non-inverted Three-State Outputs
8T98		16	v17								Hex Buffer with inverted Three-State Outputs
8T125		20	v22								Octal Bus Transceiver, inverting Outputs
8T245		20	v17								Octal Buffers
9H50		14	v16						7450		Dual 2-Wide 2-input AND-OR-INVERT Gate (74H50)
9H51		14	v15						7451		Dual 2-Wide 2-input AND-OR-INVERT Gate (74H51)
Am25LS07		16	v20								6-Bit Register with Clock Enable
Am25LS08		16	v20								4-bit Register, Clock enable and complementary Outputs
Am25LS09		16	v20								Quad 2-input Multiplexer, storage
Am25S10		16	v20								4-bit Shifter
Am25LS14		16	v23								8-bit by 1-bit two's complement Multipliers
Am25LS15		20	v20								Quad serial Adder/Subtractor
Am25S18		16	v24								Quad D Register with Standard and Three-State Outputs
Am25LS22		20	v20								8-Bit Shift Register, Sign Extend
Am25LS23		20	v20								8-bit Bidirectional Universal Shift/Storage Register, synchronous Clear
Am25LS2518		16	v20								4-bit D-Type Register
Am25LS2519		20	v21								4-bit D-Type Register with two Outputs
Am25LS2521		20	v20								8-bit Magnitude Comparator, enable
Am2946		20	v24								Octal Bus Transceiver, inverting Outputs (=Am7307)
Am2947		20	v24								Octal Bus Transceiver, non-inverting Outputs (=Am7308)
Am29520A		24	v28								Multilevel Pipeline Registers
Am29521A		24	v28								Multilevel Pipeline Registers
Am29827		24	v24								10-bit Buffer, non-inverting
Am29828		24	v24								10-bit Buffer, inverting
Am29841		24	v24								10-bit D-Type Flip-Flop
Am29842		24	v24								10-bit D-Type Flip-Flop, inverting inputs
Am29843		24	v24								9-bit D Flip-Flops, Clear and Set inputs
Am29844		24	v24								9-bit D Flip-Flops, Clear and Set inputs, inverting inputs
Am29845		24	v24								8-bit D Flip-Flops, Clear and Set inputs
Am29846		24	v24								8-bit D Flip-Flops, Clear and Set inputs, inverting inputs
Am7303		20	v14								Octal Bus Transceiver, inverting Outputs
Am7304		20	v14								Octal Bus Transceiver, non-inverting Outputs
Am7307		20	v20								Octal Bus Transceiver, inverting Outputs
Am7308		20	v20								Octal Bus Transceiver, non-inverting Outputs
Am78121		20	v20								8-bit Magnitude Comparator, enable
Am81LS95		20	v17								Octal Buffer, non-inverting, common enable
Am81LS96		20	v17								Octal Buffer, inverting, common enable
Am81LS97		20	v17								Octal Buffer, non-inverting, enable for 4 Buffers each
Am81LS98		20	v17								Octal Buffer, inverting, enable for 4 Buffers each
Am8303		20	v14								Octal Bus Transceiver, inverting Outputs (=Am7303)
Am8304		20	v14								Octal Bus Transceiver, non-inverting Outputs (=Am7304)
Am8307		20	v20	KR559IP13	K555IP13		ИП13				Octal Bus Transceiver, inverting Outputs
Am8308		20	v20	KR559IP14	K555IP14		ИП13				Octal Bus Transceiver, non-inverting Outputs
Am93S10		16	v20								Synchronous 4-Bit Decade Counter with asynchronous Clear
Am93S16		16	v20								Synchronous 4-Bit Binary Counter with asynchronous Clear
Am9341		24	v20								4-Bit Arithmetic Logic Unit and Function Generator

Identifier	J	Pins	Status	UdSSR	UdSSR	DDR	Cyrillic	Phillips	Siemens	Setting	Remark
MC3482	20	v24								MC6882	Octal Register, inverting Outputs (=MC6882)
MC4015	16	v28									Quad Type D Flip-Flop
MC6880	16	v17									Quad Bus Driver/Receiver Inverting Outputs (=8T26)
MC6882	20	v24									Octal Register, inverting Outputs (=3482)
MC6885	16	v17									Hex Buffer with non-inverted Three-State Outputs (=8T95)
MC6886	16	v17									Hex Buffer with inverted Three-State Outputs (=8T96)
MC6887	16	v17									Hex Buffer with non-inverted Three-State Outputs (=8T97)
MC6888	16	v17									Hex Buffer with inverted Three-State Outputs (=8T98)
MC6889	16	v17									Quad Bus Driver/Receiver (=8T28)
MC14495	16	v28									Hexadecimal-to-seven segment Latch / Decoder LED Driver
DS1630	14	v18									Hex TTL Buffer
DS1631	8	v18									Dual AND high power (insert at position 6)
DS1632	8	v18									Dual NAND high power (insert at position 6)
DS1633	8	v18									Dual OR high power (insert at position 6)
DS1634	8	v18									Dual NOR high power (insert at position 6)
DS3630	14	v18									Hex TTL Buffer
DS3631	8	v18									Dual AND high power (insert at position 6)
DS3632	8	v18									Dual NAND high power (insert at position 6)
DS3633	8	v18									Dual OR high power (insert at position 6)
DS3634	8	v18									Dual NOR high power (insert at position 6)
DS3662	16	v20									Quad NOR Unified Driver (=DS8641)
DS16149	16	v24									Hex Buffer with inverted Three-State Outputs
DS16179	16	v24									Hex Buffer with inverted Three-State Outputs
DS36149	16	v24								DS16149	Hex Buffer with inverted Three-State Outputs (=DS16149)
DS36179	16	v24								DS16179	Hex Buffer with inverted Three-State Outputs (=DS16179)
BA12003	16	v20									7x Darlington Arrays (=ULN200x)
CA3045	14	v22									5x NPN arrays
CA3046	14	v22									5x NPN arrays
CA3081	16	v22									7x NPN arrays (insert at position 3)
CA3082	16	v17									7x NPN arrays
CA3083	16	v22									5x NPN arrays (insert at position 3)
CA3086	14	v22									5x NPN arrays
CA3161	16	v18									BCD to 7-segment Decoder/Driver
L20x	16	v18									Quad Darlington Arrays
L70x	16	v18									7x Darlington Arrays
QS3384	24	v18									10x high-speed switch
TD6208x	18	v18									Octal Darlington Arrays (TD62081/TD62082/TD62083/TD62084)
TD6278x	18	v18									Octal Darlington Arrays (TD62783/TD62784) (insert reverse at position 8)
ULN200x	16	v14									7x Darlington Arrays (ULN2001/ULN2003/ULN2004/ULN2005)
ULN201x	16	v20									7x Darlington Arrays (ULN2011/ULN2013/ULN2014/ULN2015)
ULN202x	16	v18									7x Darlington Arrays (ULN2021/ULN2023/ULN2024/ULN2025)
ULN2064	16	v18									Quad Darlington Arrays (also ULN2066) (insert at position 5)
ULN2074	16	v18	K1109KT3				KT3				Quad Darlington Arrays (also ULN2076)
ULN280x	18	v14									Octal Darlington Arrays
ULN282x	18	v17									Octal Darlington Arrays
UDN6118	18	v17									Octal VFD Driver
UDN298x	18	v18									Octal Darlington Arrays (insert reverse at position 8)
LMx24	14	v25 (*)									Quad Operational Amplifiers LM124, LM224, LM324, LM2902 (Analog Device) (insert at position 5)
LMx39	14	v18 (*)									Quad Differential Comparators LM139, LM239, LM339 (Analog Device) (insert at position 6)
LM2900	14	v26 (*)									Quad Norton Operational Amplifiers (=LM3900)
LM3900	14	v26 (*)								LM2900	Quad Norton Operational Amplifiers (=LM3900)
uA741	8	v18 (*)									General-Purpose Operational Amplifiers (Analog Device) (insert at position 5)
FCJ121	14	v19									J-K Flip-Flop (insert reverse at position 1)
D345	16	v20									BCD to 7-segment Decoder/Driver
D346	16	v20									BCD to 7-segment Decoder/Driver
D492	14	v21									Hex digital Driver (insert at position 4)
D718	24	v21									16-bit serial-in, serial/parallel-out Shift Register, Output storage Registers (insert at position 2)
K155IE1	14	v23			K155IE1			IE1			10:1 frequency Divider (no compatible western device)
KR559IP1	16	v20			KR559IP1			ИП1			Quad 2-input NAND (no compatible western device)
KR559IP2	16	v20			KR559IP2			ИП2			Quad 2-input NOR (no compatible western device)
SNG40	14	v20									Dual 4-input NAND (= SNG 4x) (insert reverse at position 5)
SNG60	14	v20									8-input NAND (= SNG 6x) (insert reverse at position 5)
SNG90	14	v20									Dual 2-3-input AND/NOR (= SNG 0x) (insert reverse at position 5)
SNG130	14	v20									Dual 4-input NAND (= SNG 13x) (insert reverse at position 5)
SNG140	14	v20									Quad 2-input NAND (= SNG 14x) (insert reverse at position 5)
SNG150	14	v20									2-2-2-3-input AND-OR (= SNG 15x) (insert reverse at position 5)
SNG160	14	v20									Triple 2-input NAND (= SNG 16x) (insert reverse at position 5)
SNG190	14	v20									Triple 3-input NAND (= SNG 19x) (insert reverse at position 5)
SNG220	14	v20									Quad 2-input NAND (= SNG 22x) (insert reverse at position 5)
SNG230	14	v19									2-2-2-3-input AND-OR (= SNG 23x) (insert reverse at position 5)
SNG240	14	v20									Dual 4-input NAND (= SNG 24x) (insert reverse at position 5)
SNG260	14	v20									8-input NAND (= SNG 26x) (insert reverse at position 5)
SP302A	14	v20									Quad 2-input AND
SP304A	14	v20									Dual 4-input AND
SP305A	14	v20									6-input AND
SP306A	14	v20									Dual 3-input AND
SP314A	14	v20									7-input NOR
SP317A	14	v20									Dual 4-input NOR
SP334A	14	v20									Dual 4-input OR
SP337A	14	v20									Dual 4-input NAND
SP357A	14	v20									Quad 2-input NAND
SP358A	14	v20									Quad 2-input NAND
SP370A	14	v20									Triple 3-input NOR
SP374A	14	v20									Triple 3-input OR
SP375A	14	v20									Triple 2-input OR
SP377A	14	v20									Triple 3-input NAND
SP380A	14	v20									Quad 2-input NOR
SP381A	14	v20									Quad 2-input NOR
SP384A	14	v20									Quad 2-input OR
SP387A	14	v20									Quad 2-input NAND
SP391A	14	v20									Hex Inverter
CBM251641-02	28	v19									PLA Plus/4
CBM906114-01	28	v19									PLA C64
DIS1417	14	v18									Hex Display (DIS1417), visual test, returns always "Chip OK" (insert at position 8)
DL1414	8	v18									4-Character Display (DL1414), visual test (0123/****/0000), returns always "Chip OK" (insert at position 3)
DL2416	18	v18									4-Character Display (DL2416), insert reverse, visual test (0123/****/0000), returns always "Chip OK" (insert at position 6)
HP730x	8	v18									Dec Display (HP5082-7300 and HP5082-7302), visual test, returns always "Chip OK" (insert at position 6)
HP7340	8	v18									Hex Display (HP5082-7340), visual test, returns always "Chip OK" (insert at position 6)
TIL306/307	14	v19									Dec Display (TIL306/TIL307)
TIL308/309	14	v19									Dec Display (TIL308/TIL309)
TIL311	14	v18									Hex Display (TIL311), visual test, returns always "Chip OK" (insert at position 8)
VQB76	14	v22									7 Segment LED with DP
MB425	24	v17								8212	use 8212, Multi-mode Buffered 8-bit Latches (equivalent to Intel 3212/8212, 745412)
TCS012	16	v14								74367	Hex Buffer with non-inverted Three-State Outputs

Identifier	J	Pins	Status	UdSSR	UdSSR	DDR	Cyrillic	Phillips	Siemens	Setting	Remark
FJH311	14	v15								7410	Triple 3-input NAND Gate
FJH321	14	v15								7405	Hex Inverter
FLH591	14	v15								7409	Quad 2-input AND Gate with Open Collector Outputs
MH8805	8	v27								75361-8	Dual NAND high power (In DIP-8, insert at position 6)
MIC-935	14	v24								7404	Hex Inverter (DTL)
MB3614	14	v24 (*)								LMx24	Quad Operational Amplifiers LM124, LM224, LM324, LM2902 (Analog Device)
MC830F	14	v28								7420	DTL Dual 4-input NAND Gate
MC832	14	v28								7420	DTL Dual 4-input NAND Gate
MC835	14	v28								7404	DTL Hex Inverter Gate
MC836	14	v28								7404	DTL Hex Inverter Gate
MC837	14	v28								7404	DTL Hex Inverter Gate
MC838	14	v28								7407	DTL Hex Inverter Gate with Open Collector
MC840	14	v28								7404	DTL Hex Inverter Gate
MC841	14	v28								7404	DTL Hex Inverter Gate
MC846F	14	v28								7400	DTL Quad 2-input NAND Gate
MC849F	14	v28								7400	DTL Quad 2-input NAND Gate
MC857	14	v28								4011	DTL, Quad 2-input NAND Gate
MC858	14	v28								4011	DTL, Quad 2-input NAND Gate
MC861F	14	v28								7420	DTL Dual 4-input NAND Gate
MC862F	14	v28								7410	DTL Triple 2-input NAND Gate
MC863F	14	v28								7410	DTL Triple 2-input NAND Gate
MC930F	14	v28								7420	DTL Dual 4-input NAND Gate
MC932	14	v28								7420	DTL Dual 4-input NAND Gate
MC935	14	v28								7404	DTL Hex Inverter Gate
MC936	14	v28								7404	DTL Hex Inverter Gate
MC937	14	v28								7404	DTL Hex Inverter Gate
MC938	14	v28								7407	DTL Hex Inverter Gate with Open Collector
MC940	14	v28								7404	DTL Hex Inverter Gate
MC941	14	v28								7404	DTL Hex Inverter Gate
MC946F	14	v28								7400	DTL Quad 2-input NAND Gate
MC949F	14	v28								7400	DTL Quad 2-input NAND Gate
MC957	14	v28								4011	DTL, Quad 2-input NAND Gate
MC958	14	v28								4011	DTL, Quad 2-input NAND Gate
MC961F	14	v28								7420	DTL Dual 4-input NAND Gate
MC962F	14	v28								7410	DTL Triple 2-input NAND Gate
MC963F	14	v28								7410	DTL Triple 2-input NAND Gate
MC1806	14	v28								7408	DTL Quad 2-input AND Gate
MC1807	14	v28								7408	DTL Quad 2-input AND Gate
MC1808	14	v28								7432	DTL Quad 2-input OR Gate
MC1809	14	v28								7432	DTL Quad 2-input OR Gate
MC1810	14	v28								7436	DTL Quad 2-input NOR Gate
MC1811	14	v28								7436	DTL Quad 2-input NOR Gate
MC1812	14	v28								7486	DTL Quad 2-input XOR Gate
MC1818	14	v28								7400	DTL Quad 2-input XOR Gate
MC1906	14	v28								7408	DTL Quad 2-input AND Gate
MC1907	14	v28								7408	DTL Quad 2-input AND Gate
MC1908	14	v28								7432	DTL Quad 2-input OR Gate
MC1909	14	v28								7432	DTL Quad 2-input OR Gate
MC1910	14	v28								7436	DTL Quad 2-input NOR Gate
MC1911	14	v28								7436	DTL Quad 2-input NOR Gate
MC1912	14	v28								7486	DTL Quad 2-input XOR Gate
MC1918	14	v28								7400	DTL Quad 2-input XOR Gate
MC2001	14	v28								SNG140	Quad 2-input NAND (insert reverse at position 5)
MC2003	14	v28								SNG40	Dual 4-input NAND (insert reverse at position 5)
MC2005	14	v28								SNG60	8-input NAND (insert reverse at position 5)
MC2007	14	v28								SNG190	Triple 3-input NAND (insert reverse at position 5)
MC2051	14	v28								SNG140	Quad 2-input NAND (insert reverse at position 5)
MC2053	14	v28								SNG40	Dual 4-input NAND (insert reverse at position 5)
MC2057	14	v28								SNG190	Triple 3-input NAND (insert reverse at position 5)
MC2101	14	v28								SNG140	Quad 2-input NAND (insert reverse at position 5)
MC2103	14	v28								SNG40	Dual 4-input NAND (insert reverse at position 5)
MC2105	14	v28								SNG60	8-input NAND (insert reverse at position 5)
MC2107	14	v28								SNG190	Triple 3-input NAND (insert reverse at position 5)
MC2151	14	v28								SNG140	Quad 2-input NAND (insert reverse at position 5)
MC2153	14	v28								SNG40	Dual 4-input NAND (insert reverse at position 5)
MC2157	14	v28								SNG190	Triple 3-input NAND (insert reverse at position 5)
MC3000	14	v28								7400	Quad 2-Input NAND Gate
MC3001	14	v28								7408	Quad 2-Input AND Gate
MC3002	14	v28								7436	Quad 2-Input NOR Gate
MC3003	14	v28								7432	Quad 2-Input OR Gate
MC3004	14	v28								74H01	Quad 2-Input NAND Gate (Open Collector)
MC3005	14	v28								7410	Triple 3-Input NAND Gate
MC3006	14	v28								7411	Triple 3-Input AND Gate
MC3007	14	v28								7412	Triple 3-Input NAND Gate (Open Collector)
MC3008	14	v28								7404	Hex Inverter
MC3009	14	v28								7405	Hex Inverter (Open Collector)
MC3010	14	v28								7420	Dual 4-Input NAND Gate
MC3011	14	v28								7421	Dual 4-Input AND Gate
MC3012	14	v28								7422	Dual 4 input NAND Gate (Open Collector)
MC3015	14	TBD									8-Input NAND Gate
MC3016	14	v28								7430	8-Input NAND Gate
MC3018	14	v28								7462	4-Wide 3-2-2-3 input Expander
MC3019	14	v28								7461	Triple 3-Input Expander
MC3020	14	v28								7450	Expandable Dual2-Wide 2-Input AOI Gate
MC3023	14	v28								7451	Dual 2-Wide 2-Input AOI Gate
MC3024	14	v28								7440	Dual4-Input NAND Buffer
MC3030	14	v28								7460	Dual 4-Input Expander
MC3031	14	v28								7452	Expandable 4-Wide 2-2-2-3 input AND-OR Gate
MC3032	14	v28								74H53	Expandable 4-Wide 2-2-2-3 input AOI Gate
MC3033	14	v28								74H54	4-Wide 2-2-2-3 input AOI Gate
MC3034	14	v28								74H55	Expandable 2 -Wide 4-1 nput AOI Gate
MC3054	14	v28								74H71	J-K Flip-Flop
MC3055	14	v28								7472	J-K Flip-Flop
MC3060	14	v28								7474	Dual Type D Flip-Flop
MC3061	14	TBD									Dual J-K Flip-Flop
MC3062	14	TBD									Dual J-K Flip-Flop
MC3063	14	v28								7473	Dual J-K Flip-Flop
MC3301	14	v28								LM2900	Quad Norton Operational Amplifiers (=LM3900)
55001	14	v15								7400	Quad 2-input NAND Gate
55002	14	v15								7402	Quad 2-input NOR Gate
55003	14	v15								7404	Hex Inverter
55005	14	v15								7410	Triple 3-input NAND Gate
55007	14	v14								7430	8-input NAND Gate
55008	16	v14								7442	Binary-Coded Decimal

Identifier	J	Pins	Status	UdSSR	UdSSR	DDR	Cyrillic	Philips	Siemens	Setting	Remark
55010		14	v16							7450	Dual 2-Wide 2-input AND-OR-INVERT Gate
55011		14	v14							7474	Dual D Positive Edge triggered Flip-Flop with Preset and Clear
55019		16	v17							74179	4-bit parallel-access Shift Register, asynchronous Clear input, complementary Qd Output
55023		16	v14							73153	Dual 4-Line to 1-Line Data Selector/Multiplexer
55024		16	v19							74161	Synchronous 4-Bit Binary Counter with asynchronous Clear
55028		14	v14							74164	8-Bit Parallel-Out Serial Shift Register with asynchronous Clear
55029		14	v15							7454	2-2-2-2-input AND-OR-INVERT Gate (54 only)
55032		14	v14							7401	Quad 2-input NAND Gate with Open Collector Outputs
55034		14	v14							7440	Dual 4-input NAND Gate
uPC844		14	v25 (*)							LMx24	Quad Operational Amplifiers LM124, LM224, LM324, LM2902 (Analog Device) (insert at position 5)
8870		14	n/a								Hex LED Digit Driver (DS8870)
9601		14	n/a								Retriggerable monostable Multivibrator